

P70-NAD6

P70/P5 DIP SWITCHES SETTING : 1(Pulse/ICT104U)

Supported bill N\$ 10, 20, 30, 50, 100, 200 6bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / N\$ 10	OFF	OFF	OFF							
	2 Pulse / N\$ 10	OFF	OFF	ON							
	3 Pulse / N\$ 10	OFF	ON	OFF							
	4 Pulse / N\$ 10	OFF	ON	ON							
	5 Pulse / N\$ 10	ON	OFF	OFF							
	10 Pulse / N\$ 10	ON	OFF	ON							
	20 Pulse / N\$ 10	ON	ON	OFF							
	100 Pulse / N\$ 10	ON	ON	ON							
	Fast output Pulse <small>Lo= 50ms Hi=100ms</small>				ON						
★	Slow output Pulse <small>Lo= 50ms Hi=300ms</small>				OFF						
	Inhibit level Active Low				ON						
	Inhibit level Active High				OFF						
★	Accept N\$ 10				ON						
★	Reject N\$ 10				OFF						
★	Accept N\$ 20 & 30				ON						
	Reject N\$ 20 & 30				OFF						
★	Accept N\$ 50				ON						
	Reject N\$ 50				OFF						
★	Accept N\$ 100				ON						
	Reject N\$ 100				OFF						
★	Accept N\$ 200				ON						
	Reject N\$ 200				OFF						

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

DIP SWITCHES SETTING : 2 Currency Assign Data

	FUNCTION	SW1	SW2	SW3	SW4	Interface Bill value	Pulse	ICT104U
★	Credit-Pulse Normal High	ON				BV1	N\$ 10	N\$ 10
	Credit-Pulse Normal Low	OFF						
★	Pulse Protocol		ON			BV2	N\$ 20	N\$ 20
	ICT104U Protocol		OFF					
	Harness Disable				ON	BV3	N\$ 30	N\$ 30
★	Harness Enable				OFF	BV4	N\$ 50	N\$ 50
	Reserved				ON	BV5	N\$ 100	N\$ 100
★	Reserved				OFF	BV6	N\$ 200	N\$ 200

★ Manufacture setting

Note: (1) Please reset the bill acceptor after any changes on Dip switch.

(2) Dip switches 1 & 3 are only used for pulse protocol.