

# PHP6

## P70/P5 DIP SWITCHES SETTING : 1(Pulse/ICT)

Supported bill P 20, 50, 100, 200, 500, 1000 6bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10	
★	1 Pulse / P 10	OFF	OFF	OFF								
	2 Pulse / P 10	OFF	OFF	ON								
	3 Pulse / P 10	OFF	ON	OFF								
	4 Pulse / P 10	OFF	ON	ON								
	5 Pulse / P 10	ON	OFF	OFF								
	10 Pulse / P 10	ON	OFF	ON								
	20 Pulse / P 10	ON	ON	OFF								
	100 Pulse / P 10	ON	ON	ON								
	Fast output Pulse Lo= 50ms Hi=100ms											ON
★	Slow output Pulse Lo= 50ms Hi=300ms											OFF
	Inhibit level Active Low				ON							
★	Inhibit level Active High				OFF							
★	Accept P 20 & 50					ON						
	Reject P 20 & 50					OFF						
★	Accept P 100					ON						
	Reject P 100					OFF						
★	Accept P 200					ON						
	Reject P 200					OFF						
★	Accept P 500						ON					
	Reject P 500						OFF					
★	Accept P 1000							ON				
	Reject P 1000							OFF				

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

# P70-PHP6(Pulse/ICT)

## DIP SWITCHES SETTING : 2

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Protocol		ON		
	ICT Protocol		OFF		
	Harness Disable			ON	
★	Harness Enable			OFF	
	Manufacture Default				ON
★	System Default				OFF

★ Manufacture setting

## Currency Assign Data

Interface Bill value	Pulse	ICT
BV1	20	20
BV2	50	50
BV3	100	100
BV4	200	200
BV5	500	500
BV6	1000	1000