



VND3

P70/P5 DIP SWITCHES SETTING : 1(Pulse/ICT)

Supported bill VND 10000, 20000, 50000

3bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / VND 10000	OFF	OFF	OFF							
	2 Pulse / VND 10000	OFF	OFF	ON							
	3 Pulse / VND 10000	OFF	ON	OFF							
	4 Pulse / VND 10000	OFF	ON	ON							
	5 Pulse / VND 10000	ON	OFF	OFF							
	10 Pulse / VND 10000	ON	OFF	ON							
	20 Pulse / VND 10000	ON	ON	OFF							
	100 Pulse / VND 10000	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept VND 10000				ON						
	Reject VND 10000				OFF						
★	Accept VND 20000						ON				
	Reject VND 20000						OFF				
★	Accept VND 50000							ON			
	Reject VND 50000							OFF			
	Reserved									ON	
★	Reserved									OFF	
	Reserved										ON
★	Reserved									OFF	

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

DIP SWITCHES SETTING : 2

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Protocol		ON		
	ICT Protocol		OFF		
	Harness Disable			ON	
★	Harness Enable			OFF	
	Manufacture Default				ON
★	System Default				OFF

★ Manufacture setting

