



DKK5

P77/P5 DIP SWITCHES SETTING : 1

Supported bill DKK 50(99, 05), 100(99, 02), 200(03),
500(97, 03), 1000(98, 04) 5bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / DKK 50	OFF	OFF	OFF							
	2 Pulse / DKK 50	OFF	OFF	ON							
	3 Pulse / DKK 50	OFF	ON	OFF							
	4 Pulse / DKK 50	OFF	ON	ON							
	5 Pulse / DKK 50	ON	OFF	OFF							
	10 Pulse / DKK 50	ON	OFF	ON							
	20 Pulse / DKK 50	ON	ON	OFF							
	100 Pulse / DKK 50	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low					ON					
★	Inhibit level Active High					OFF					
★	Accept DKK 50						ON				
	Reject DKK 50						OFF				
★	Accept DKK 100							ON			
	Reject DKK 100							OFF			
★	Accept DKK 200								ON		
	Reject DKK 200								OFF		
★	Accept DKK 500									ON	
	Reject DKK 500									OFF	
★	Accept DKK 1000										ON
	Reject DKK 1000										OFF

★ Manufacture setting

Note: (1)Please reset the bill acceptor after set the dip switch.

(2)Dip switches 1 to 5 are only used for pulse protocol.

DIP SWITCHES SETTING : 2

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
	Pulse Protocol		ON		
	ICT Protocol		OFF		
	HOLD			ON	
				OFF	
	Ignore Sensor Problem(Note 1)				ON
★	Acknowledge Sensor Problem (Note 2)				OFF

★ Manufacture setting

Note : (1) Sensor 6 problem occurred ==>> BA will be still in working order.

(The face LED will be flashing in short green about 2 seconds everytime you restart BA.)

(2) BA will stop to work when it acknowledges Sensor 6 problem occurred.

(The face LED will be flashing in red.)

