

# P77-GBP2

## P77/P5 DIP SWITCHES SETTING : 1(Pulse/ccTalk)

### Supported bill

- 【England】 Bank of England : 5、10 2bills**
- 【Scotland】 Bank of Scotland : 5、10 2bills**
- Clydesdale Bank : 5、10 2bills**
- Royal Bank of Scotland : 5、10 2bills**
- 【Northern Ireland】 Bank of Ireland : 5、10 2bills**
- Ulster Bank : 5、10 2bills**
- Danske Bank:10 1bills**
- First Trust Bank : 10 1bills**

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / £ 5	OFF	OFF	OFF							
	2 Pulse / £ 5	OFF	OFF	ON							
	3 Pulse / £ 5	OFF	ON	OFF							
	4 Pulse / £ 5	OFF	ON	ON							
	5 Pulse / £ 5	ON	OFF	OFF							
	10 Pulse / £ 5	ON	OFF	ON							
	20 Pulse / £ 5	ON	ON	OFF							
	100 Pulse / £ 5	ON	ON	ON							
	Fast output Pulse <small>Lo= 50ms Hi=100ms</small>				ON						
★	Slow output Pulse <small>Lo= 50ms Hi=300ms</small>				OFF						
	Inhibit level Active Low					ON					
★	Inhibit level Active High					OFF					
★	Accept All £ 5 bills						ON				
	Reject All £ 5 bills						OFF				
★	Accept All £ 10 bills							ON			
	Reject All £ 10 bills							OFF			
★	Reserved								ON		
	Reserved								OFF		
★	Reserved									ON	
	Reserved									OFF	
★	Reserved										ON
	Reserved										OFF

(★) Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

# P77-GBP2/P5(Pulse/ccTalk)

## DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal High	ON			
	Credit-Pulse Normal Low	OFF			
★	Pulse Protocol		ON		
	ccTalk Protocol		OFF		
	Harness Disable			ON	
★	Harness Enable			OFF	
	Reserved				ON
★	Reserved				OFF

(★) Manufacture setting

## DIP SWITCHES SETTING : 3(ccTalk)

	FUNCTION	SW1	SW2	SW3	SW4
★	Encryption MODE	ON			
	Decrypt MODE	OFF			
	Pulse Protocol		ON		
★	ccTalk Protocol		OFF		
	ccTalk Parameters Reset			ON	
★	Keep ccTalk Parameters			OFF	
	Reserved				ON
★	Reserved				OFF

(★) Manufacture setting

Note:(1) Please reset the bill acceptor after set the dip switch.

(2) ccTalk Parameters Reset

Put this switch to on and reset power will restore the ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

\*This has to be done after finished calibration process.

## Currency Assign Data

Interface Bill value	Pulse	ccTalk
BV1	£ 5	£ 5
BV2	£ 10	£ 10