

## P77-HRK5

### P77/P5 DIP SWITCHES SETTING : 1(Pulse/ICT104)

Supported bill KUNA 10, 20, 50, 100, 200 5bills.

|   | FUNCTION                                  | SW1 | SW2 | SW3 | SW4 | SW5 | SW6 | SW7 | SW8 | SW9 | SW10 |
|---|-------------------------------------------|-----|-----|-----|-----|-----|-----|-----|-----|-----|------|
| ★ | 1 Pulse / KUNA 10                         | OFF | OFF | OFF |     |     |     |     |     |     |      |
|   | 2 Pulse / KUNA 10                         | OFF | OFF | ON  |     |     |     |     |     |     |      |
|   | 3 Pulse / KUNA 10                         | OFF | ON  | OFF |     |     |     |     |     |     |      |
|   | 4 Pulse / KUNA 10                         | OFF | ON  | ON  |     |     |     |     |     |     |      |
|   | 5 Pulse / KUNA 10                         | ON  | OFF | OFF |     |     |     |     |     |     |      |
|   | 10 Pulse / KUNA 10                        | ON  | OFF | ON  |     |     |     |     |     |     |      |
|   | 20 Pulse / KUNA 10                        | ON  | ON  | OFF |     |     |     |     |     |     |      |
|   | 100 Pulse / KUNA 10                       | ON  | ON  | ON  |     |     |     |     |     |     |      |
|   | Fast output Pulse<br>Lo= 50ms<br>Hi=100ms |     |     |     | ON  |     |     |     |     |     |      |
| ★ | Slow output Pulse<br>Lo= 50ms<br>Hi=300ms |     |     |     | OFF |     |     |     |     |     |      |
|   | Inhibit level Active Low                  |     |     |     | ON  |     |     |     |     |     |      |
| ★ | Inhibit level Active High                 |     |     |     | OFF |     |     |     |     |     |      |
| ★ | Accept KUNA 10                            |     |     |     | ON  |     |     |     |     |     |      |
|   | Reject KUNA 10                            |     |     |     | OFF |     |     |     |     |     |      |
| ★ | Accept KUNA 20                            |     |     |     | ON  |     |     |     |     |     |      |
|   | Reject KUNA 20                            |     |     |     | OFF |     |     |     |     |     |      |
| ★ | Accept KUNA 50                            |     |     |     | ON  |     |     |     |     |     |      |
|   | Reject KUNA 50                            |     |     |     | OFF |     |     |     |     |     |      |
| ★ | Accept KUNA 100                           |     |     |     | ON  |     |     |     |     |     |      |
|   | Reject KUNA 100                           |     |     |     | OFF |     |     |     |     |     |      |
| ★ | Accept KUNA 200                           |     |     |     | ON  |     |     |     |     |     |      |
|   | Reject KUNA 200                           |     |     |     | OFF |     |     |     |     |     |      |

★ Manufacture setting

Note: (1)Please reset the bill acceptor after set the dip switch.

(2)Dip switches 1 to 5 are only used for pulse protocol.

### DIP SWITCHES SETTING : 2

### Currency Assign Data

|   | FUNCTION          | SW1 | SW2 | SW3 | SW4 |
|---|-------------------|-----|-----|-----|-----|
| ★ | Pulse Normal High | ON  |     |     |     |
|   | Pulse Normal Low  | OFF |     |     |     |
| ★ | Pulse Protocol    |     | ON  |     |     |
|   | ICT Protocol      |     | OFF |     |     |
|   | Harness Disable   |     |     | ON  |     |
| ★ | Harness Enable    |     |     | OFF |     |
| ★ | Reserved          |     |     |     | ON  |
|   |                   |     |     |     | OFF |

★ Manufacture setting

| Interface<br>Bill value | ICT | Pulse |
|-------------------------|-----|-------|
| BV1                     | 10  | 10    |
| BV2                     | 20  | 20    |
| BV3                     | 50  | 50    |
| BV4                     | 100 | 100   |
| BV5                     | 200 | 200   |