



INR6

P77/P5 DIP SWITCHES SETTING : 1

Supported bill Rs 10, 20, 50, 100(96, 05), 500(old, 00, 06), 1000(00, 05) 6bills.

Note: 500, 1000 is not taken by P77/P5.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / Rs 10	OFF	OFF	OFF							
2 Pulse / Rs 10	OFF	OFF	ON							
3 Pulse / Rs 10	OFF	ON	OFF							
4 Pulse / Rs 10	OFF	ON	ON							
5 Pulse / Rs 10	ON	OFF	OFF							
10 Pulse / Rs 10	ON	OFF	ON							
20 Pulse / Rs 10	ON	ON	OFF							
100 Pulse / Rs 10	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low				ON						
Inhibit level Active High				OFF						
★ Accept Rs 10 & 20				ON						
Reject Rs 10 & 20				OFF						
★ Accept Rs 50				ON						
Reject Rs 50				OFF						
★ Accept Rs 100				ON						
Reject Rs 100				OFF						
★ Accept Rs 500				ON						
Reject Rs 500				OFF						
★ Accept Rs 1000				ON						
Reject Rs 1000				OFF						

★ Manufacture setting

Note: (1)Please reset the bill acceptor after set the dip switch.

(2)Dip switches 1 to 5 are only used for pulse protocol.

DIP SWITCHES SETTING : 2

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
Pulse Protocol		ON		
ICT Protocol		OFF		
HOLD			ON	
			OFF	
Ignore Sensor Problem(Note 1)			ON	
★ Acknowledge Sensor Problem (Note 2)			OFF	

★ Manufacture setting

Note : (1) Sensor 6 problem occurred ==>> BA will be still in working order.

(The face LED will be flashing in short green about 2 seconds everytime you restart BA.)

(2) BA will stop to work when it acknowledges Sensor 6 problem occurred.

(The face LED will be flashing in red.)

