



INR7

P77 DIP SWITCHES SETTING : 1(Pulse/ MDB)

Supported bill Rs 5, 10, 20, 50, 100, 500, 1000 7bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10	
★	1 Pulse / Rs 5	OFF	OFF	OFF								
	2 Pulse / Rs 5	OFF	OFF	ON								
	3 Pulse / Rs 5	OFF	ON	OFF								
	4 Pulse / Rs 5	OFF	ON	ON								
	5 Pulse / Rs 5	ON	OFF	OFF								
	10 Pulse / Rs 5	ON	OFF	ON								
	20 Pulse / Rs 5	ON	ON	OFF								
	100 Pulse / Rs 5	ON	ON	ON								
	Fast output Pulse Lo= 50ms Hi=100ms											ON
★	Slow output Pulse Lo= 50ms Hi=300ms											OFF
	Inhibit level Active Low					ON						
★	Inhibit level Active High					OFF						
★	Accept Rs 5 & 10 & 20						ON					
	Reject Rs 5 & 10 & 20						OFF					
★	Accept Rs 50							ON				
	Reject Rs 50							OFF				
★	Accept Rs 100								ON			
	Reject Rs 100								OFF			
★	Accept Rs 500									ON		
	Reject Rs 500									OFF		
★	Accept Rs 1000										ON	
	Reject Rs 1000										OFF	

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Mode		ON		
	MDB Interface		OFF		
	Harness Disable			ON	
★	Harness Enable			OFF	
	Manufacture Default				ON
★	System Default				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Mode		ON		
★	MDB Interface		OFF		
	Reserved			ON	
★				OFF	
	Manufacture Default				ON
★	System Default				OFF

★ Manufacture setting