

P77-PKR7

P77/P5 DIP SWITCHES SETTING : 1(Pulse/MDB)

Supported bill PKR 10, 20, 50, 100, 500, 1000, 5000 7 bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / Rp 10	OFF	OFF	OFF							
	2 Pulse / Rp 10	OFF	OFF	ON							
	3 Pulse / Rp 10	OFF	ON	OFF							
	4 Pulse / Rp 10	OFF	ON	ON							
	5 Pulse / Rp 10	ON	OFF	OFF							
	10 Pulse / Rp 10	ON	OFF	ON							
	20 Pulse / Rp 10	ON	ON	OFF							
	100 Pulse / Rp 10	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low					ON					
★	Inhibit level Active High					OFF					
★	Accept Rp 10 & 20						ON				
	Reject Rp 10 & 20						OFF				
★	Accept Rp 50 & 100							ON			
	Reject Rp 50 & 100							OFF			
★	Accept Rp 500								ON		
	Reject Rp 500								OFF		
★	Accept Rp 1000									ON	
	Reject Rp 1000									OFF	
★	Accept Rp 5000										ON
	Reject Rp 5000										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

P77-PKR7(Pulse/MDB)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Mode		ON		
	MDB Interface		OFF		
	Harness Disable			ON	
★	Harness Enable			OFF	
	Manufacture Default				ON
★	System Default				OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 & 3 are only used for pulse protocol.

DIP SWITCHES SETTING : 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Mode		ON		
★	MDB Interface		OFF		
	Reserved			ON	
★				OFF	
	Manufacture Default				ON
★	System Default				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	MDB	Pulse
BV1	Rp 10	Rp 10
BV2	Rp 20	Rp 20
BV3	Rp 50	Rp 50
BV4	Rp 100	Rp 100
BV5	Rp 500	Rp 500
BV6	Rp 1000	Rp 1000
BV7		Rp 5000