

UAH7**P77/P5 DIP SWITCHES SETTING : 1(Pulse/RS232 A0)**

Supported bill H 5, 10, 20, 50, 100, 200, 500 7bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / H 5	OFF	OFF	OFF							
	2 Pulses / H 5	OFF	OFF	ON							
	3 Pulses / H 5	OFF	ON	OFF							
	4 Pulses / H 5	OFF	ON	ON							
	5 Pulses / H 5	ON	OFF	OFF							
	10 Pulses / H 5	ON	OFF	ON							
	20 Pulses / H 5	ON	ON	OFF							
	100 Pulses / H 5	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low					ON					
★	Inhibit level Active High					OFF					
★	Accept H 5 & 10						ON				
	Reject H 5 & 10						OFF				
★	Accept H 20 & 50							ON			
	Reject H 20 & 50							OFF			
★	Accept H 100								ON		
	Reject H 100								OFF		
★	Accept H 200									ON	
	Reject H 200									OFF	
★	Accept H 500										ON
	Reject H 500										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

P77-UAH7/P5(Pulse/RS232 A0)**DIP SWITCHES SETTING : 2(Pulse)**

	FUNCTION	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Protocol		ON		
	RS232 A0 Protocol		OFF		
	Harness Disable			ON	
★	Harness Enable			OFF	
	Manufacture Default				ON
★	System Default				OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 & 3 are only used for pulse protocol.

DIP SWITCHES SETTING : 2(RS232 A0)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Protocol		ON		
★	RS232 A0 Protocol		OFF		
	Reserved			ON	
★	Reserved			OFF	
	Manufacture Default				ON
★	System Default				OFF

★ Manufacture setting