

UZS3

P85/P5 DIP SWITCHES SETTING : 1(Pulse/ICT)

Supported bill Som 500, 1000, 5000

3 bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / 500 Som	OFF	OFF	OFF							
2 Pulse / 500 Som	OFF	OFF	ON							
3 Pulse / 500 Som	OFF	ON	OFF							
4 Pulse / 500 Som	OFF	ON	ON							
5 Pulse / 500 Som	ON	OFF	OFF							
10 Pulse / 500 Som	ON	OFF	ON							
20 Pulse / 500 Som	ON	ON	OFF							
100 Pulse / 500 Som	ON	ON	ON							
★ Fast output Pulse <small>Lo= 50ms Hi=100ms</small>				ON						
★ Slow output Pulse <small>Lo= 50ms Hi=300ms</small>				OFF						
★ Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept Som 500						ON				
Reject Som 500						OFF				
★ Accept Som 1000							ON			
Reject Som 1000							OFF			
★ Accept Som 5000								ON		
Reject Som 5000								OFF		
★ Reserved									ON	
★ Reserved									OFF	
Som 5000 : 15 Pulse <small>(Note.3)</small>										ON
★ Normal										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

(3) When turn ON the dip Switch 10, Som 5000 have 10 Pulse.

When turn OFF the dip Switch 10, Som 5000 have 15 Pulse.

DIP SWITCHES SETTING : 2

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
★ Pulse Mode		ON		
ICT104 Mode		OFF		
★ Harness Disable			ON	
Harness Enable			OFF	
★ Manufacture Default				ON
System Default				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	ICT104
BV1	Som 500	Som 500
BV2	Som 1000	Som 1000
BV3	Som 5000	Som 5000