

P85-UZS5

P85/P5 DIP SWITCHES SETTING : 1(Pulse/ccNet/RS232 A0)

Supported bill Som 1000, 5000, 10000, 50000, 100000 5bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / Som 1000	OFF	OFF	OFF							
2 Pulses / Som 1000	OFF	OFF	ON							
3 Pulses / Som 1000	OFF	ON	OFF							
4 Pulses / Som 1000	OFF	ON	ON							
5 Pulses / Som 1000	ON	OFF	OFF							
10 Pulses / Som 1000	ON	OFF	ON							
20 Pulses / Som 1000	ON	ON	OFF							
100 Pulses / Som 1000	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept Som 1000						ON				
Reject Som 1000						OFF				
★ Accept Som 5000 & 10000 & 50000							ON			
Reject Som 5000 & 10000 & 50000							OFF			
★ Accept Som 100000								ON		
Reject Som 100000								OFF		
★ High Security									ON	
High Acceptance									OFF	
★ Normal										ON
★ Special Pulse (Reject Som 50000 & 100000)										OFF

(★) Manufacture setting

Note:(1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

(3) When turn ON the dip Switch 10: When turn OFF the dip Switch 10:

Som 1000 have 1 Pulses. Som 1000 have 1 Pulses.

Som 5000 have 5 Pulses. Som 5000 have 8 Pulses.

Som 10000 have 10 Pulses. Som 10000 have 20 Pulses.

Som 50000 have 50 Pulses.

Som 100000 have 100 Pulses.

P85-UZS5/P5(Pulse/ccNet/RS232 A0)

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Protocol		ON		
Other Protocol		OFF		
Harness Disable			ON	
★ Harness Enable			OFF	
Reserved				ON
★ Reserved				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ccNet)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Protocol		ON		
★ Other Protocol		OFF		
Reserved			ON	
★ Reserved			OFF	
★ ccNet Protocol (SW2 OFF)				ON
RS232 A0 Protocol				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(RS232 A0)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON		
★ Other Protocol		OFF		
Reserved			ON	
★ Reserved			OFF	
ccNet Protocol				ON
★ RS232 A0 Protocol(SW2 OFF)				OFF

★ Manufacture setting

RS232 A0 INFORMATION	
BillType Data	
Code	Denomination
1	Reserved
2	Reserved
3	Reserved
4	Som 1000
5	Som 5000
6	Som 10000
7	Som 50000
8	Som 100000

Currency Assign Data

Interface Bill value	ccNet	Pulse	RS232 A0
BV1	Som 1000	Som 1000	Som 1000
BV2	Som 5000	Som 5000	Som 5000
BV3	Som 10000	Som 10000	Som 10000
BV4	Som 50000	Som 50000	Som 50000
BV5	Som 100000	Som 100000	Som 100000