

Item	Nation	Dipswitch Setting							Channel / Recognizable currency																																																																																																																						
1	Chile	SW1	SW1:OFF SW2:OFF = Pulse Width(25ms) SW1:ON SW2:OFF = Pulse Width(45ms)							Channel[1] 10 pesos																																																																																																																					
		SW2	SW1:OFF SW2:ON = Pulse Width(60ms) SW1:ON SW2:ON = Pulse Width(100ms)							Channel[2] 50 pesos																																																																																																																					
		SW3	Reserved							Channel[3] 100 pesos (Old)																																																																																																																					
		SW4	Pulse Ratio Setting (*Note1)							Channel[4] 100 pesos (New)																																																																																																																					
		SW5								Channel[5] 500 pesos																																																																																																																					
		SW6								Channel[6]																																																																																																																					
		SW7	ON : Normal mode ; OFF : Self-learning mode(*Note2)							Channel[7]																																																																																																																					
		SW8	ON : Normal Open ; OFF : Normal Close							Channel[8]																																																																																																																					
		<table border="1"> <thead> <tr> <th colspan="9">*Note1: Pulse Ratio Setting</th> </tr> </thead> <tbody> <tr> <td>SW6</td> <td>OFF</td> <td>ON</td> <td>OFF</td> <td>ON</td> <td>OFF</td> <td>ON</td> <td>OFF</td> <td>ON</td> </tr> <tr> <td>SW5</td> <td>OFF</td> <td>OFF</td> <td>ON</td> <td>ON</td> <td>OFF</td> <td>OFF</td> <td>ON</td> <td>ON</td> </tr> <tr> <td>SW4</td> <td>OFF</td> <td>OFF</td> <td>OFF</td> <td>OFF</td> <td>ON</td> <td>ON</td> <td>ON</td> <td>ON</td> </tr> <tr> <th colspan="9">Number of Coins : Number of Pulse</th> </tr> <tr> <td>CH1</td> <td>2:1</td> <td>4:1</td> <td>1:1</td> <td>1:1</td> <td>2:1</td> <td>2:1</td> <td>2:1</td> <td>1:1</td> </tr> <tr> <td>CH2</td> <td>1:1</td> <td>2:1</td> <td>1:1</td> <td>1:1</td> <td>1:1</td> <td>1:1</td> <td>1:1</td> <td>1:5</td> </tr> <tr> <td>CH3</td> <td>1:1</td> <td>2:1</td> <td>1:2</td> <td>1:2</td> <td>1:1</td> <td>1:3</td> <td>1:2</td> <td>1:10</td> </tr> <tr> <td>CH4</td> <td>1:2</td> <td>1:1</td> <td>1:4</td> <td>1:2</td> <td>1:2</td> <td>1:6</td> <td>1:5</td> <td>1:10</td> </tr> <tr> <td>CH5</td> <td>1:4</td> <td>1:2</td> <td>1:8</td> <td>1:4</td> <td>1:5</td> <td>1:12</td> <td>1:6</td> <td>1:50</td> </tr> <tr> <td>CH6</td> <td>1:5</td> <td>1:2</td> <td>1:8</td> <td>1:4</td> <td>N/A</td> <td>N/A</td> <td>1:10</td> <td>N/A</td> </tr> <tr> <td>CH7</td> <td>1:8</td> <td>1:4</td> <td>1:10</td> <td>1:10</td> <td>N/A</td> <td>N/A</td> <td>1:12</td> <td>N/A</td> </tr> <tr> <td>CH8</td> <td>1:10</td> <td>1:5</td> <td>1:10</td> <td>1:10</td> <td>N/A</td> <td>N/A</td> <td>N/A</td> <td>N/A</td> </tr> </tbody> </table>									*Note1: Pulse Ratio Setting									SW6	OFF	ON	OFF	ON	OFF	ON	OFF	ON	SW5	OFF	OFF	ON	ON	OFF	OFF	ON	ON	SW4	OFF	OFF	OFF	OFF	ON	ON	ON	ON	Number of Coins : Number of Pulse									CH1	2:1	4:1	1:1	1:1	2:1	2:1	2:1	1:1	CH2	1:1	2:1	1:1	1:1	1:1	1:1	1:1	1:5	CH3	1:1	2:1	1:2	1:2	1:1	1:3	1:2	1:10	CH4	1:2	1:1	1:4	1:2	1:2	1:6	1:5	1:10	CH5	1:4	1:2	1:8	1:4	1:5	1:12	1:6	1:50	CH6	1:5	1:2	1:8	1:4	N/A	N/A	1:10	N/A	CH7	1:8	1:4	1:10	1:10	N/A	N/A	1:12	N/A	CH8	1:10	1:5	1:10	1:10	N/A	N/A	N/A	N/A
		*Note1: Pulse Ratio Setting																																																																																																																													
SW6	OFF	ON	OFF	ON	OFF	ON	OFF	ON																																																																																																																							
SW5	OFF	OFF	ON	ON	OFF	OFF	ON	ON																																																																																																																							
SW4	OFF	OFF	OFF	OFF	ON	ON	ON	ON																																																																																																																							
Number of Coins : Number of Pulse																																																																																																																															
CH1	2:1	4:1	1:1	1:1	2:1	2:1	2:1	1:1																																																																																																																							
CH2	1:1	2:1	1:1	1:1	1:1	1:1	1:1	1:5																																																																																																																							
CH3	1:1	2:1	1:2	1:2	1:1	1:3	1:2	1:10																																																																																																																							
CH4	1:2	1:1	1:4	1:2	1:2	1:6	1:5	1:10																																																																																																																							
CH5	1:4	1:2	1:8	1:4	1:5	1:12	1:6	1:50																																																																																																																							
CH6	1:5	1:2	1:8	1:4	N/A	N/A	1:10	N/A																																																																																																																							
CH7	1:8	1:4	1:10	1:10	N/A	N/A	1:12	N/A																																																																																																																							
CH8	1:10	1:5	1:10	1:10	N/A	N/A	N/A	N/A																																																																																																																							
*Note2: Enter self-learning mode (Re-set the UCA3 after setting up)																																																																																																																															
SW7		OFF																																																																																																																													
Channel setting for acceptable coins in the self-learning mode																																																																																																																															
Channel	CH1	CH2	CH3	CH4	CH5	CH6	CH7	CH8																																																																																																																							
SW6	OFF	ON	OFF	ON	OFF	ON	OFF	ON																																																																																																																							
SW5	OFF	OFF	ON	ON	OFF	OFF	ON	ON																																																																																																																							
SW4	OFF	OFF	OFF	OFF	ON	ON	ON	ON																																																																																																																							
Reset self-learning mode (Re-set the UCA3 after setting up)																																																																																																																															
SW7		OFF→ON→OFF																																																																																																																													