

A6/V6-SAR2

A6/V6 Option Switch Settings

Supported bill SRIs 1, 5 2bills.

A6/V6 dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject SRIs 1	ON											
★ Accept SRIs 1	OFF											
★ Reject SRIs 5		ON										
★ Accept SRIs 5		OFF										
★ Reserved			ON									
★ Reserved			OFF									
★ Reserved				ON								
★ Reserved				OFF								
★ Reserved					ON							
★ Reserved					OFF							
★ High Acceptance					ON							
★ High Security					OFF							
★ Harness Disable						ON						
★ Harness Enable						OFF						
★ Inhibit Active High							ON					
★ Inhibit Active Low							OFF					
★ 1 pulse / SRIs 1								OFF	OFF			
★ 2 pulse / SRIs 1								ON	OFF			
★ 4 pulse / SRIs 1								OFF	ON			
★ 20 pulse / SRIs 1								ON	ON			
★ Pulse Speed	50ms LO / 50ms HI								OFF	OFF		
	60ms LO / 300ms HI								ON	OFF		
	30ms LO / 50ms HI								OFF	ON		
	150ms LO / 150ms HI								ON	ON		

◆ Factory configuration has all switches in the OFF position.

Note : (1) Reset the bill acceptor after setting the dip switch.

(2) SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

A6/V6-SAR2

A6 Interface Settings: 2(Pulse/RS232)

INTERFACE	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON		
RS232 Interface		OFF		
★ Reserved			ON	
			OFF	
				ON
				OFF

★ Manufacture setting

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON		
★ RS232 Interface		OFF		
★ Reserved			ON	
			OFF	
				ON
				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	RS232
BV1	SRIs 1	SRIs 1
BV2	SRIs 5	SRIs 5

V6 Interface Settings: 2(M.D.B)

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
★ Reserved		ON		
★ M.D.B Interface		OFF		
★ Reserved			ON	
			OFF	
				ON
				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	MDB
BV1	SRIs 1
BV2	SRIs 5