

A6/V6 Option Switch Settings: 1

Supported bill SDP 1

1bill.

A6/V6 dip-switch settings and functions:

| FUNCTION | SW1 | SW2 | SW3 | SW4 | SW5 | SW6 | SW7 | SW8 | SW1 | SW2 | SW3 | SW4 |
|-------------------------------|----------------------|-----|-----|-----|-----|-----|-----|-----|-----|-----|-----|-----|
| ★ Reject SDP 1 | ON | | | | | | | | | | | |
| ★ Accept SDP 1 | OFF | | | | | | | | | | | |
| ★ Reserved | | ON | | | | | | | | | | |
| ★ Reserved | | OFF | | | | | | | | | | |
| ★ Reserved | | | ON | | | | | | | | | |
| ★ Reserved | | | OFF | | | | | | | | | |
| ★ Reserved | | | | ON | | | | | | | | |
| ★ Reserved | | | | OFF | | | | | | | | |
| ★ Reserved | | | | | ON | | | | | | | |
| ★ Reserved | | | | | OFF | | | | | | | |
| ★ Reserved | | | | | | ON | | | | | | |
| ★ Reserved | | | | | | OFF | | | | | | |
| ★ Harness Disable | | | | | | | ON | | | | | |
| ★ Harness Enable | | | | | | | OFF | | | | | |
| ★ Inhibit Active High | | | | | | | | ON | | | | |
| ★ Inhibit Active Low | | | | | | | | OFF | | | | |
| ★ 1 pulse / SDP 1 | | | | | | | | | OFF | OFF | | |
| ★ 2 pulses / SDP 1 | | | | | | | | | ON | OFF | | |
| ★ 5 pulses / SDP 1 | | | | | | | | | OFF | ON | | |
| ★ 20 pulses / SDP 1 | | | | | | | | | ON | ON | | |
| ★ Interface Timing Conversion | 50ms on / 50ms off | | | | | | | | OFF | OFF | | |
| | 60ms on / 300ms off | | | | | | | | ON | OFF | | |
| | 30ms on / 50ms off | | | | | | | | OFF | ON | | |
| | 150ms on / 150ms off | | | | | | | | ON | ON | | |

★ Manufacture setting

◆ Factory configuration has all switches in the OFF position.

Note : (1) Reset the bill acceptor after setting the dip switch.

(2) SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

A6 Interface Settings: 2(Pulse/RS232)

| INTERFACE | SW1 | SW2 | SW3 | SW4 |
|----------------------------|-----|-----|-----|-----|
| ★ Credit-Pulse Normal HIGH | ON | | | |
| Credit-Pulse Normal LOW | OFF | | | |
| ★ Pulse Mode | | ON | | |
| RS232 Interface | | OFF | | |
| ★ Reserved | | | ON | |
| | | | OFF | |
| | | | | ON |
| | | | | OFF |

★ Manufacture setting

| INTERFACE | SW1 | SW2 | SW3 | SW4 |
|-----------------|-----|-----|-----|-----|
| ★ Reserved | ON | | | |
| | OFF | | | |
| Pulse Mode | | ON | | |
| RS232 Interface | | OFF | | |
| ★ Reserved | | | ON | |
| | | | OFF | |
| | | | | ON |
| | | | | OFF |

★ Manufacture setting

V6 Interface Settings: 2(MDB)

| INTERFACE | SW1 | SW2 | SW3 | SW4 |
|---|-----|-----|-----|-----|
| ★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2 | ON | | | |
| | OFF | | | |
| Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0 | | | | |
| ★ Reserved | | ON | | |
| ★ MDB Interface | | OFF | | |
| ★ Reserved | | | ON | |
| | | | OFF | |
| | | | | ON |
| | | | | OFF |

★ Manufacture setting