

## A7/V7-ROL3

### A7/V7 Option Switch Settings : 1(Pulse/Parallel/MDB)

Supported bill Lei 1, 5, 10 3bills.

A7/V7 dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject Lei 1	ON											
	Accept Lei 1	OFF											
	Reject Lei 5		ON										
★	Accept Lei 5		OFF										
	Reject Lei 10			ON									
★	Accept Lei 10			OFF									
	Reserved				ON								
★	Reserved				OFF								
	Reserved				ON								
★	Reserved				OFF								
	High Acceptance				ON								
★	High Security				OFF								
	Harness Disable					ON							
★	Harness Enable					OFF							
	Inhibit Active High						ON						
★	Inhibit Active Low						OFF						
★	1 pulse / Lei 1								OFF	OFF			
	2 pulse / Lei 1								ON	OFF			
	5 pulse / Lei 1								OFF	ON			
	20 pulse / Lei 1								ON	ON			
★	Pulse Speed	50ms on / 50ms off								OFF		OFF	
		60ms on / 300ms off								ON		OFF	
		30ms on / 50ms off								OFF		ON	
		150ms on / 150ms off								ON		ON	

◆ Factory configuration has all switches in the OFF position.

Note : (1) Reset the bill acceptor after setting the dip switch.

(2) SW6 . SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

## A7/V7-ROL3

### Interface Settings: 2(Pulse)

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Interface		ON	OFF	
	Parallel Interface		OFF	ON	
	MDB Interface		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

### Interface Settings: 3(Parallel)

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Interface		ON	OFF	
★	Parallel Interface		OFF	ON	
	MDB Interface		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

### Interface Settings: 4(MDB)

	INTERFACE	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 2	ON			
	Decimal Point Position (DPP) = 100				
	Scaling Factor (SF) = 1	OFF			
	Decimal Point Position (DPP) = 0				
	Pulse Interface		ON	OFF	
	Parallel Interface		OFF	ON	
★	MDB Interface		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting