

V7-THB3

V7 Option Switch Settings : 1(Pulse/Special MDB)

Supported bill THB 20, 50, 100

3 bills.

V7 dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject THB 20	ON											
★	Accept THB 20	OFF											
★	Reject THB 50		ON										
★	Accept THB 50		OFF										
★	Reject THB 100			ON									
★	Accept THB 100			OFF									
★	Reserved				ON								
★	Reserved				OFF								
★	Reserved				ON								
★	Reserved				OFF								
★	Reserved				ON								
★	Reserved				OFF								
★	Harness disable						ON						
★	Harness enable						OFF						
★	Inhibit Active High							ON					
★	Inhibit Active Low							OFF					
★	1 pulse / THB 10								OFF	OFF			
★	2 pulses / THB 10								ON	OFF			
★	4 pulses / THB 10								OFF	ON			
★	20 pulses / THB 10								ON	ON			
★	Pulse Speed	50ms LO / 50ms HI								OFF	OFF		
		60ms LO / 300ms HI								ON	OFF		
		30ms LO / 50ms HI								OFF	ON		
		150ms LO / 150ms HI								ON	ON		

◆ Factory configuration has all switches in the OFF position.

Note : (1) Reset the bill acceptor after setting the dip switch.

(2) SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

V7-THB3(Pulse/Special MDB)

V7 Interface Settings: 2 (Pulse)

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON		
	MDB Interface (Note)		OFF		
★	Reserved			ON	
				OFF	
					ON
					OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	MDB	Pulse
BV1	THB 20	THB 20
BV2	THB 50	THB 50
BV3	THB 100	THB 100

V7 Interface Settings: 3 (Special MDB)

	INTERFACE	SW1	SW2	SW3	SW4
★	Decimal Point Position (DPP) = 2	ON			
	Divided by 10 (Special Function)	OFF			
	Pulse Mode		ON		
★	MDB Interface (Note)		OFF		
★	Reserved			ON	
				OFF	
					ON
					OFF

★ Manufacture setting

Note: Please refer to the dip-switch #1 of internal dip-switch for MDB Decimal Point Setup.

if SW3 Dip1=ON, \$20 shows 20.00, \$50 shows 50.00 to VMC

if SW3 Dip1=OFF,\$20 shows 2, \$50 shows 5 to VMC