

V77E-AMD2

V77E Option Switch Settings : 1(Pulse/ICT104V/ICT104U/MDB)

Supported bill AMD 1000, 2000 2bills.

V77E dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject AMD 1000	ON											
	Accept AMD 1000	OFF											
	Reject AMD 2000		ON										
★	Accept AMD 2000		OFF										
	Reserved			ON									
★	Reserved			OFF									
	Reserved				ON								
★	Reserved				OFF								
	Reserved					ON							
★	Reserved					OFF							
	Reserved						ON						
★	Reserved					OFF							
	Harness Disable							ON					
★	Harness Enable							OFF					
	Inhibit Active High								ON				
★	Inhibit Active Low								OFF				
★	1 pulse / AMD 1000									OFF	OFF		
	2 pulses / AMD 1000									ON	OFF		
	4 pulses / AMD 1000									OFF	ON		
	20 pulses / AMD 1000									ON	ON		
★	Pulse Speed	50ms LO / 50ms HI									OFF	OFF	
		60ms LO / 300ms HI									ON	OFF	
		30ms LO / 50ms HI									OFF	ON	
		150ms LO / 150ms HI									ON	ON	

★ Manufacture setting

Note : (1) Default setting.

(2) Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.

(3) Remove the front cover and the dip-switch in on the CPU board.

V77E-AMD2(Pulse/ICT104V/ICT104U/MDB)

Interface Settings: 2(Pulse)

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Interface		ON	OFF	
	ICT104V Interface		OFF	ON	
	MDB Interface		ON	ON	
	ICT104U Interface		OFF	OFF	
	Reserved				ON
★					OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	MDB	ICT104V	ICT104U
BV1	AMD 1000	AMD 1000	AMD 1000	AMD 1000
BV2	AMD 2000	AMD 2000	AMD 2000	AMD 2000

Interface Settings: 2(ICT104V)

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Interface		ON	OFF	
★	ICT104V Interface		OFF	ON	
	MDB Interface		ON	ON	
	ICT104U Interface		OFF	OFF	
	Reserved				ON
★					OFF

★ Manufacture setting

Interface Settings: 2(ICT104U)

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Interface		ON	OFF	
	ICT104V Interface		OFF	ON	
	MDB Interface		ON	ON	
★	ICT104U Interface		OFF	OFF	
	Reserved				ON
★					OFF

★ Manufacture setting

Interface Settings: 2(MDB)

	INTERFACE	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Interface		ON	OFF	
	ICT104V Interface		OFF	ON	
★	MDB Interface		ON	ON	
	ICT104U Interface		OFF	OFF	
	Reserved				ON
★					OFF

★ Manufacture setting