

V77E-BYR7

V77E Option Switch Settings : 1(Pulse/MDB/ccNet)

Supported bill BYR 500, 1000, 5000, 10000, 20000, 50000, 100000 7bills.

V77E dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
	Reject Ruble 500 & 1000	ON											
★	Accept Ruble 500 & 1000	OFF											
	Reject Ruble 5000 & 10000		ON										
★	Accept Ruble 5000 & 10000		OFF										
	Reject Ruble 20000			ON									
★	Accept Ruble 20000			OFF									
	Reject Ruble 50000				ON								
★	Accept Ruble 50000				OFF								
	Reject Ruble 100000				ON								
★	Accept Ruble 100000				OFF								
	Reserved					ON							
★	Reserved					OFF							
	Harness Disable						ON						
★	Harness Enable						OFF						
	Inhibit Active High							ON					
★	Inhibit Active Low							OFF					
★	1 pulse / Ruble 500								OFF	OFF			
	2 pulse / Ruble 500								ON	OFF			
	5 pulse / Ruble 500								OFF	ON			
	20 pulse / Ruble 500								ON	ON			
★	Pulse Speed	50ms on / 50ms off									OFF	OFF	
		60ms on / 300ms off									ON	OFF	
		30ms on / 50ms off									OFF	ON	
		150ms on / 150ms off									ON	ON	

★ Manufacture setting

◆ Factory configuration has all switches in the OFF position.

Note : (1) Reset the bill acceptor after setting the dip switch.

(2) SW6.SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

V77E-BYR7(Pulse/MDB/ccNet)

Interface Settings: 2(Pulse)

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Interface		ON	OFF	
	MDB Interface		OFF	ON	
	CCNet Interface		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

Interface Settings: 3(MDB)

	INTERFACE	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 10 Decimal Point Position (DPP) = 1	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Interface		ON	OFF	
★	MDB Interface		ON	ON	
	CCNet Interface		OFF	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

Interface Settings: 4(CCNet)

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Interface		ON	OFF	
	MDB Interface		ON	ON	
★	CCNet Interface		OFF	ON	
★	Reserved				ON
					OFF

★ Manufacture setting