

V77E-CHF4

V77E Option Switch Settings : 1(Pulse/ICT104U/MDB)

Supported bill \$F 10, 20, 50, 100 4 bills.

V77E dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject \$F 10	ON											
	Accept \$F 10	OFF											
	Reject \$F 20		ON										
★	Accept \$F 20		OFF										
	Reject \$F 50			ON									
★	Accept \$F 50			OFF									
	Reject \$F 100				ON								
★	Accept \$F 100				OFF								
	Reserved				ON								
★	Reserved				OFF								
	Reserved				ON								
★	Reserved				OFF								
	Harness Disable					ON							
★	Harness Enable					OFF							
	Inhibit Active High						ON						
★	Inhibit Active Low						OFF						
★	1 pulse / \$F 10							OFF	OFF				
	5 pulse / \$F 10							ON	OFF				
	10 pulse / \$F 10							OFF	ON				
	20 pulse / \$F 10							ON	ON				
★	Pulse Speed	50ms HI / 50ms LO						OFF		OFF			
		60ms HI / 300ms LO						ON		OFF			
		30ms HI / 50ms LO						OFF		ON			
		150ms HI / 150ms LO						ON		ON			

★ Manufacture setting

◆ Factory configuration has all switches in the OFF position.

Note : (1) Reset the bill acceptor after setting the dip switch.

(2) SW6.SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

V77E-CHF4(Pulse/ICT104U/MDB)

DIP SWITCHES SETTING : 3(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Mode		ON	OFF	
	ICT104U Interface		OFF	ON	
	MDB Interface		ON	ON	
	Reserved		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 3(ICT104U)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON	OFF	
★	ICT104U Interface		OFF	ON	
	MDB Interface		ON	ON	
	Reserved		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 3(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Mode		ON	OFF	
	ICT104U Interface		OFF	ON	
★	MDB Interface		ON	ON	
	Reserved		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

Note 1: Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.

2: Remove the front cover and the dip-switch in on the CPU board.

Currency Assign Data

Interface Bill value	ICT104U	Pulse	MDB
BV1	\$F 10	\$F 10	\$F 10
BV2	\$F 20	\$F 20	\$F 20
BV3	\$F 50	\$F 50	\$F 50
BV4	\$F 100	\$F 100	\$F 100