

## V77E-JPY4

### V77E Option Switch Settings : 1(Pulse/RS232 A0)

Supported bill ¥ 1000, 2000, 5000, 10000 4bills.

V77E dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject ¥ 1000	ON											
★	Accept ¥ 1000	OFF											
	Reject ¥ 2000		ON										
★	Accept ¥ 2000		OFF										
	Reject ¥ 5000			ON									
★	Accept ¥ 5000			OFF									
	Reject ¥ 10000				ON								
★	Accept ¥ 10000				OFF								
	Reserved				ON								
★	Reserved				OFF								
	Reserved					ON							
★	Reserved					OFF							
	Harness Disable						ON						
★	Harness Enable						OFF						
	Inhibit Active High							ON					
★	Inhibit Active Low							OFF					
★	1 pulse / ¥ 1000								OFF	OFF			
	2 pulses / ¥ 1000								ON	OFF			
	5 pulses / ¥ 1000								OFF	ON			
	20 pulses / ¥ 1000								ON	ON			
★	Pulse Speed	50ms on / 50ms off									OFF	OFF	
		60ms on / 300ms off									ON	OFF	
		30ms on / 50ms off									OFF	ON	
		150ms on / 150ms off									ON	ON	

★ Manufacture setting

## V77E-JPY4(Pulse/RS232 A0)

### DIP SWITCHES SETTING : 2 (Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Mode		ON		
	RS232 A0 Interface		OFF		
★	Reserved			ON	
				OFF	
					ON
★					OFF

★ Manufacture setting

### DIP SWITCHES SETTING : 3 (RS232 A0)

	FUNCTION	SW1	SW2	SW3	SW4
	Reserved	ON			
★		OFF			
	Pulse Mode		ON		
★	RS232 A0 Interface		OFF		
★	Reserved			ON	
				OFF	
					ON
★					OFF

RS232 A0 INFORMATION	
BillType Data	
Code	Denomination
1	Reserved
2	Reserved
3	Reserved
4	1000
5	2000
6	5000
7	10000
8	Reserved
9	Reserved

★ Manufacture setting

Factory configuration has all switches in the OFF position.

Note : (1) Default setting.

(2) Use 2nd dip of the internal dip-switch to change different interface protocol.

(3) Remove the front cover and the dip-switch in on the CPU board.

(Please refer to "SW1" setting.)