

V77E-KZT5

V77E Option Switch Settings : 1(Pulse/RS232 A0/ccNet/ICT104U)

Supported bill KZT 200, 500, 1000, 2000, 5000 5bills.

V77E dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject KZT 200	ON											
★ Accept KZT 200	OFF											
Reject KZT 500		ON										
★ Accept KZT 500		OFF										
Reject KZT 1000			ON									
★ Accept KZT 1000			OFF									
Reject KZT 2000				ON								
★ Accept KZT 2000				OFF								
Reject KZT 5000					ON							
★ Accept KZT 5000					OFF							
Reserved					ON							
★ Reserved					OFF							
Harness Disable							ON					
★ Harness Enable							OFF					
Inhibit Active High								ON				
★ Inhibit Active Low								OFF				
★ 1 pulse / KZT 100									OFF	OFF		
2 pulses / KZT 100									ON	OFF		
5 pulses / KZT 100									OFF	ON		
20 pulses / KZT 100									ON	ON		
★ Pulse Speed		50ms LO / 50ms HI								OFF	OFF	
		60ms LO / 300ms HI								ON	OFF	
		30ms LO / 50ms HI								OFF	ON	
		150ms LO / 150ms HI								ON	ON	

★ Manufacture setting

◆ Factory configuration has all switches in the OFF position.

Note : (1) Reset the bill acceptor after setting the dip switch.

(2) SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

(3) Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.

V77E-KZT5(Pulse/RS232 A0/ccNet/ICT104U)

Interface Settings: 2(Pulse)

INTERFACE	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Interface		ON	OFF	
RS232 A0 Interface		OFF	ON	
ccNet Interface		ON	ON	
ICT104U Interface		OFF	OFF	
Reserved				ON
★ Reserved				OFF

★ Manufacture setting

Interface Settings: 2(ccNet)

INTERFACE	SW1	SW2	SW3	SW4
19200 Baud rate	ON			
★ 9600 Baud rate	OFF			
Pulse Interface		ON	OFF	
RS232 A0 Interface		OFF	ON	
★ ccNet Interface		ON	ON	
ICT104U Interface		OFF	OFF	
Reserved				ON
★ Reserved				OFF

★ Manufacture setting

Interface Settings: 2(RS232 A0)

INTERFACE	SW1	SW2	SW3	SW4
Reserved	ON			
★ Reserved	OFF			
Pulse Interface		ON	OFF	
★ RS232 A0 Interface		OFF	ON	
ccNet Interface		ON	ON	
ICT104U Interface		OFF	OFF	
Reserved				ON
★ Reserved				OFF

★ Manufacture setting

RS232 A0 INFORMATION

Bill Type Data	
Code	Denomination
1	KZT 200
2	KZT 500
3	KZT 1000
4	KZT 2000
5	KZT 5000

Interface Settings: 2(ICT104U)

INTERFACE	SW1	SW2	SW3	SW4
Reserved	ON			
★ Reserved	OFF			
Pulse Interface		ON	OFF	
RS232 A0 Interface		OFF	ON	
ccNet Interface		ON	ON	
★ ICT104U Interface		OFF	OFF	
Reserved				ON
★ Reserved				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	RS232 A0	ccNet	ICT104U
BV1	KZT 200	KZT 200	KZT 200	KZT 200
BV2	KZT 500	KZT 500	KZT 500	KZT 500
BV3	KZT 1000	KZT 1000	KZT 1000	KZT 1000
BV4	KZT 2000	KZT 2000	KZT 2000	KZT 2000
BV5	KZT 5000	KZT 5000	KZT 5000	KZT 5000