

V77E-MAD4

V77E Option Switch Settings: 1(Pulse/ICT104U/MDB)

Supported bill MAD 20, 50, 100, 200 4bills.

V77E dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject MAD 20	ON											
★ Accept MAD 20	OFF											
Reject MAD 50		ON										
★ Accept MAD 50		OFF										
Reject MAD 100			ON									
★ Accept MAD 100			OFF									
Reject MAD 200				ON								
★ Accept MAD 200				OFF								
Reserved					ON							
★ Reserved					OFF							
Reserved						ON						
★ Reserved						OFF						
Harness Disable							ON					
★ Harness Enable							OFF					
Inhibit Active High								ON				
★ Inhibit Active Low								OFF				
★ 1 pulse / MAD 10									OFF	OFF		
2 pulses / MAD 10									ON	OFF		
4 pulses / MAD 10									OFF	ON		
20 pulses / MAD 10									ON	ON		
★ Pulse Speed		50ms on / 50ms off									OFF	OFF
		60ms on / 300ms off									ON	OFF
		30ms on / 50ms off									OFF	ON
		150ms on / 150ms off									ON	ON

★ Manufacture setting

Note : (1) Please reset the bill acceptor after any changes on Dip switch.

(2) SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

V77E-MAD4(Pulse/ICT104U/MDB)

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
★ Pulse Mode		ON	OFF	
ICT104U Interface		OFF	ON	
MDB Interface		ON	ON	
Reserved		OFF	OFF	
★ Reserved				ON
				OFF

DIP SWITCHES SETTING : 2(ICT104U) Currency Assign Data

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Interface		OFF	ON	
MDB Interface		ON	ON	
Reserved		OFF	OFF	
★ Reserved				ON
				OFF

Interface Bill value	Pulse	ICT	MDB
BV1	MAD 20	MAD 20	MAD 20
BV2	MAD 50	MAD 50	MAD 50
BV3	MAD 100	MAD 100	MAD 100
BV4	MAD 200	MAD 200	MAD 200

DIP SWITCHES SETTING : 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Interface		OFF	ON	
MDB Interface		ON	ON	
Reserved		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

Note 1: Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.