

V77E-UAH9

V77E Option Switch Settings: 1(Pulse/ICT104U/MDB)

Supported bill H 1, 2, 5, 10, 20, 50, 100, 200, 500 9bills.

V77E dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject H 1 & 2 (Note.4)	ON											
★	Accept H 1 & 2 (Note.4)	OFF											
★	Reject H 5 & 10		ON										
★	Accept H 5 & 10		OFF										
★	Reject H 20 & 50			ON									
★	Accept H 20 & 50			OFF									
★	Reject H 100				ON								
★	Accept H 100				OFF								
★	Reject H 200					ON							
★	Accept H 200					OFF							
★	Reject H 500						ON						
★	Accept H 500						OFF						
★	Harness Disable							ON					
★	Harness Enable							OFF					
★	Inhibit Active High								ON				
★	Inhibit Active Low								OFF				
★	1 pulse / H 1 & 5 (Note.4)									OFF	OFF		
★	5 pulses / H 1 & 5 (Note.4)									ON	OFF		
★	10 pulses / H 1 & 5 (Note.4)									OFF	ON		
★	20 pulses / H 1 & 5 (Note.4)									ON	ON		
★	Pulse Speed	50ms LO / 50ms HI								OFF		OFF	
		60ms LO / 300ms HI								ON		OFF	
		30ms LO / 50ms HI								OFF		ON	
		150ms LO / 150ms HI								ON		ON	

★ Manufacture setting

Note : (1) Default setting

(2) Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.

(3) Remove the front cover and the dip-switch in on the CPU board.

(4) Pulse Mode: When Dip 1 is OFF,One Pulse per UAH 1.

When Dip 1 is ON,One Pulse per UAH 5.

MDB Mode: When Dip 1 is OFF,Reject UAH 500.

When Dip 1 is ON,Accept UAH 500.

V77E-UAH9(Pulse/ICT104U/MDB)

DIP SWITCHES SETTING : 3(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Mode		ON	OFF	
	ICT104U Interface		OFF	ON	
	MDB Interface		ON	ON	
	Reserved		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 3(ICT104U)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON	OFF	
★	ICT104U Interface		OFF	ON	
	MDB Interface		ON	ON	
	Reserved		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	ICT104U	Pulse		MDB	
		When Dip 1 is OFF	When Dip 1 is ON	When Dip 1 is OFF	When Dip 1 is ON
BV1	H 1	H 1	H 5	H 1	H 5
BV2	H 2	H 2	H 10	H 2	H 10
BV3	H 5	H 5	H 20	H 5	H 20
BV4	H 10	H 10	H 50	H 10	H 50
BV5	H 20	H 20	H 100	H 20	H 100
BV6	H 50	H 50	H 200	H 50	H 200
BV7	H 100	H 100	H 500	H 100	H 500
BV8	H 200	H 200		H 200	
BV9	H 500	H 500			

DIP SWITCHES SETTING : 4(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Mode		ON	OFF	
	ICT104U Interface		OFF	ON	
★	MDB Interface		ON	ON	
	Reserved		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting