

V7E/LX7-OMR3

V7E/LX7 Option Switch Settings: 1(Pulse/ICT104U/M.D.B)

Supported bill OMR 0.1, 0.5, 1 3bills.

V7E dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject OMR 0.1	ON											
	Accept OMR 0.1	OFF											
★	Reject OMR 0.5		ON										
★	Accept OMR 0.5		OFF										
★	Reject OMR 1			ON									
★	Accept OMR 1			OFF									
	Reserved			ON									
★	Reserved			OFF									
	Reserved				ON								
★	Reserved				OFF								
	Reserved				ON								
★	Reserved				OFF								
	Pulse Mode	Other Mode											
	Harness Disable	BA stops working when fishing						ON					
★	Harness Enable	Normal						OFF					
	Inhibit Active High								ON				
★	Inhibit Active Low								OFF				
★	1 pulse / OMR 0.1								OFF	OFF			
	5 pulse / OMR 0.1								ON	OFF			
	10 pulse / OMR 0.1								OFF	ON			
	25 pulse / OMR 0.1								ON	ON			
★	Pulse Speed	50ms LO / 50ms HI									OFF	OFF	
		60ms LO / 300ms HI									ON	OFF	
		30ms LO / 50ms HI									OFF	ON	
		150ms LO / 150ms HI									ON	ON	

★ Manufacture setting

◆ Note : (1) Reset the bill acceptor after setting the dip switch.

(2) SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

V7E/LX7-OMR3(Pulse/ICT104U/M.D.B)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Mode		ON	OFF	
	ICT104U Interface		OFF	ON	
	MDB Interface		ON	ON	
	Reserved		OFF	OFF	
★	Reserved				ON
					OFF

DIP SWITCHES SETTING : 2(ICT104U)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON	OFF	
★	ICT104U Interface		OFF	ON	
	MDB Interface		ON	ON	
	Reserved		OFF	OFF	
★	Reserved				ON
					OFF

Currency Assign Data

Interface Bill value	ICT	Pulse	MDB
BV1	OMR 0.1	OMR 0.1	OMR 0.1
BV2	OMR 0.5	OMR 0.5	OMR 0.5
BV3	OMR 1	OMR 1	OMR 1

DIP SWITCHES SETTING : 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 3	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 1	OFF			
	Pulse Mode		ON	OFF	
	ICT Interface		OFF	ON	
★	MDB Interface		ON	ON	
	Reserved		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

Note 1: Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.

2: Remove the front cover and the dip-switch in on the CPU board.