

V7E Option Switch Settings: 1(Pulse/ICT/M.D.B)

Supported bill Kuna 10, 20, 50, 100, 200 5 bills.

V7E dip-switch settings and functions:

| FUNCTION | SW1 | SW2 | SW3 | SW4 | SW5 | SW6 | SW7 | SW8 | SW1 | SW2 | SW3 | SW4 |
|-----------------------|----------------------|-----|-----|-----|-----|-----|-----|-----|-----|-----|-----|-----|
| ★ Reject Kuna 10 | ON | | | | | | | | | | | |
| ★ Accept Kuna 10 | OFF | | | | | | | | | | | |
| ★ Reject Kuna 20 | | ON | | | | | | | | | | |
| ★ Accept Kuna 20 | | OFF | | | | | | | | | | |
| ★ Reject Kuna 50 | | | ON | | | | | | | | | |
| ★ Accept Kuna 50 | | | OFF | | | | | | | | | |
| ★ Reject Kuna 100 | | | | ON | | | | | | | | |
| ★ Accept Kuna 100 | | | | OFF | | | | | | | | |
| ★ Reject Kuna 200 | | | | | ON | | | | | | | |
| ★ Accept Kuna 200 | | | | | OFF | | | | | | | |
| ★ Reserved | | | | | | ON | | | | | | |
| ★ Reserved | | | | | | OFF | | | | | | |
| ★ Harness Disable | | | | | | | ON | | | | | |
| ★ Harness Enable | | | | | | | OFF | | | | | |
| ★ Inhibit Active High | | | | | | | | ON | | | | |
| ★ Inhibit Active Low | | | | | | | | OFF | | | | |
| ★ 1 pulse / Kuna 10 | | | | | | | | | OFF | OFF | | |
| 5 pulse / Kuna 10 | | | | | | | | | ON | OFF | | |
| 10 pulse / Kuna 10 | | | | | | | | | OFF | ON | | |
| 20 pulse / Kuna 10 | | | | | | | | | ON | ON | | |
| ★ Pulse Speed | 50ms on / 50ms off | | | | | | | | OFF | OFF | | |
| | 60ms on / 300ms off | | | | | | | | ON | OFF | | |
| | 30ms on / 50ms off | | | | | | | | OFF | ON | | |
| | 150ms on / 150ms off | | | | | | | | ON | ON | | |

★ Manufacture setting

◆ Note : (1) Reset the bill acceptor after setting the dip switch.

(2) SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

DIP SWITCHES SETTING : 2(Pulse)

| | FUNCTION | SW1 | SW2 | SW3 | SW4 |
|---|-------------------|-----|-----|-----|-----|
| ★ | Pulse Normal High | ON | | | |
| | Pulse Normal Low | OFF | | | |
| | ICT Interface | | OFF | ON | |
| ★ | Pulse Mode | | ON | OFF | |
| | M.D.B Interface | | ON | ON | |
| ★ | Reserved | | | | ON |
| | | | | | OFF |

DIP SWITCHES SETTING : 3(ICT)

| | FUNCTION | SW1 | SW2 | SW3 | SW4 |
|---|-----------------|-----|-----|-----|-----|
| ★ | Reserved | ON | | | |
| | | OFF | | | |
| ★ | ICT Interface | | OFF | ON | |
| | Pulse Mode | | ON | OFF | |
| | M.D.B Interface | | ON | ON | |
| ★ | Reserved | | | | ON |
| | | | | | OFF |

DIP SWITCHES SETTING : 4(M.D.B)

| | FUNCTION | SW1 | SW2 | SW3 | SW4 |
|---|---------------------------------------------------------------|-----|-----|-----|-----|
| ★ | Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2 | ON | | | |
| | Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0 | OFF | | | |
| | ICT Interface | | OFF | ON | |
| | Pulse Mode | | ON | OFF | |
| ★ | M.D.B Interface | | ON | ON | |
| ★ | Reserved | | | | ON |
| | | | | | OFF |

★ Manufacture setting

- ◆ 1.Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.
- 2.Remove the front cover and the dip-switch in on the CPU board.