

## V7E/LX7-EGP2

### V7E/LX7 Option Switch Settings: 1(Pulse/ICT104U/RS232 A0/ccNet)

**Supported bill EGP 5, 10 2 bills.**

V7E/LX7 dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject EGP 5	ON											
	Accept EGP 5	OFF											
	Reject EGP 10		ON										
★	Accept EGP 10		OFF										
	Reserved			ON									
★	Reserved			OFF									
	Reserved				ON								
★	Reserved				OFF								
	Reserved					ON							
★	Reserved					OFF							
	Reserved						ON						
★	Reserved						OFF						
	Reserved							ON					
★	Reserved							OFF					
	Harness Disable							ON					
★	Harness Enable							OFF					
	Inhibit Active High								ON				
★	Inhibit Active Low								OFF				
★	1 pulse / EGP 5									OFF	OFF		
	2 pulses / EGP 5									ON	OFF		
	5 pulses / EGP 5									OFF	ON		
	20 pulses / EGP 5									ON	ON		
★	Pulse Speed	50ms on / 50ms off								OFF		OFF	
		60ms on / 300ms off								ON		OFF	
		30ms on / 50ms off								OFF		ON	
		150ms on / 150ms off								ON		ON	

★ Manufacture setting

Note : (1) Default setting.

## V7E/LX7-EGP2(Pulse/ICT104U/RS232 A0/ccNet)

### DIP SWITCHES SETTING: 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Mode		ON	OFF	
	ICT104U Mode		OFF	OFF	
	ccNet Mode		ON	ON	
	RS232 A0 Mode		OFF	ON	
	Reserved				ON
★					OFF

### DIP SWITCHES SETTING: 2(ICT)

	FUNCTION	SW1	SW2	SW3	SW4
	Reserved	ON			
★		OFF			
	Pulse Mode		ON	OFF	
★	ICT104U Mode		OFF	OFF	
	ccNet Mode		ON	ON	
	RS232 A0 Mode		OFF	ON	
	Reserved				ON
★					OFF

### DIP SWITCHES SETTING: 2(ccNet)

	FUNCTION	SW1	SW2	SW3	SW4
	Reserved	ON			
★	9600 Baud rate	OFF			
	Pulse Mode		ON	OFF	
	ICT104U Mode		OFF	OFF	
★	ccNet Mode		ON	ON	
	RS232 A0 Mode		OFF	ON	
	Reserved				ON
★					OFF

★ Manufacture setting

### Currency Assign Data

Interface	Pulse	RS232 A0	ccNet	ICT104U
BV1	EGP 5	EGP 5	EGP 5	EGP 5
BV2	EGP 10	EGP 10	EGP 10	EGP 10

### DIP SWITCHES SETTING: 2(RS232 A0)

	FUNCTION	SW1	SW2	SW3	SW4
	Reserved	ON			
★		OFF			
	Pulse Mode		ON	OFF	
	ICT104U Mode		OFF	OFF	
	ccNet Mode		ON	ON	
★	RS232 A0 Mode		OFF	ON	
	Reserved				ON
★					OFF

★ Manufacture setting

#### RS232 A0 INFORMATION

Bill Type Data	
Code	Denomination
1	Reserved
2	EGP 5
3	EGP 10
4	Reserved
5	Reserved
6	Reserved
7	Reserved
8	Reserved