

V7E/LX7-MYR6

V7E/LX7 Option Switch Settings: 1(Pulse/ICT104V/ICT104U/MDB)

Supported bill M\$ 1, 5, 10, 20, 50, 100 6bills.

V7E/LX7 dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject M\$ 1	ON											
★ Accept M\$ 1	OFF											
★ Reject M\$ 5		ON										
★ Accept M\$ 5		OFF										
★ Reject M\$ 10 & 20			ON									
★ Accept M\$ 10 & 20			OFF									
★ Reject M\$ 50				ON								
★ Accept M\$ 50				OFF								
★ Reject M\$ 100					ON							
★ Accept M\$ 100					OFF							
★ Reserved					ON							
★ Reserved					OFF							
★ Pulse Mode	Other Mode											
★ Harness Disable	BA stopped working when fishing				ON							
★ Harness Enable	Normal				OFF							
★ Inhibit Active High	BA stopped working when followed 4Sec				ON							
★ Inhibit Active Low	Normal				OFF							
★ 1 pulse / M\$ 1									OFF	OFF		
★ 5 pulses / M\$ 1									ON	OFF		
★ 10 pulses / M\$ 1									OFF	ON		
★ 25 pulses / M\$ 1									ON	ON		
★ Pulse Speed	50ms LO / 50ms HI								OFF	OFF		
	60ms LO / 300ms HI								ON	OFF		
	30ms LO / 50ms HI								OFF	ON		
	150ms LO / 150ms HI								ON	ON		

★ Manufacture setting

Note : (1) Default setting.

(2) Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.

(3) Remove the front cover and the dip-switch in on the CPU board.

(4) BV1=M\$1,BV3=M\$5, BV4=M\$10, BV5=M\$50, BV6=M\$100, BV7=M\$20

V7E/LX7-MYR6(Pulse/ICT104V/ICT104U/MDB)

DIP SWITCHES SETTING : 2(Pulse)

Currency Assign Data

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
★ Pulse Mode		ON	OFF	
ICT104U Interface		OFF	ON	
ICT104V Interface		ON	ON	
MDB Interface		OFF	OFF	
★ Reserved				ON
				OFF

Interface Bill value	ICT104V	ICT104U	Pulse	MDB
BV1	M\$ 1	M\$ 1	M\$ 1	M\$ 1
BV3	M\$ 5	M\$ 5	M\$ 5	M\$ 5
BV4	M\$ 10	M\$ 10	M\$ 10	M\$ 10
BV5	M\$ 50	M\$ 50	M\$ 50	M\$ 50
BV6	M\$ 100	M\$ 100	M\$ 100	M\$ 100
BV7	M\$ 20	M\$ 20	M\$ 20	M\$ 20

DIP SWITCHES SETTING : 2(ICT104U)

DIP SWITCHES SETTING : 2(ICT104V)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Interface		OFF	ON	
ICT104V Interface		ON	ON	
MDB Interface		OFF	OFF	
★ Reserved				ON
				OFF

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Interface		OFF	ON	
ICT104V Interface		ON	ON	
MDB Interface		OFF	OFF	
★ Reserved				ON
				OFF

DIP SWITCHES SETTING : 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
Pulse Mode		ON	OFF	
ICT104U Interface		OFF	ON	
ICT104V Interface		ON	ON	
MDB Interface		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

Note 1. Default setting

2. Use both 2nd and 3rd dip of the internal dip-switch to change different interface protocol.

3. Remove the front cover and the dip-switch in on the CPU board.

4. BV1=M\$1,BV3=M\$5, BV4=M\$10, BV5=M\$50, BV6=M\$100, BV7=M\$20