

V7E/LX7-RUR5

V7E/LX7 Option Switch Settings: 1(Pulse/ICT/M.D.B)

Supported bill Ruble 10, 50, 100, 500, 1000 5bills.

V7E dip-switch settings and functions:

| | FUNCTION | SW1 | SW2 | SW3 | SW4 | SW5 | SW6 | SW7 | SW8 | SW1 | SW2 | SW3 | SW4 |
|---|---------------------|----------------------|-----|-----|-----|-----|-----|-----|-----|-----|-----|-----|-----|
| ★ | Reject Ruble 10 | ON | | | | | | | | | | | |
| ★ | Accept Ruble 10 | OFF | | | | | | | | | | | |
| ★ | Reject Ruble 50 | | ON | | | | | | | | | | |
| ★ | Accept Ruble 50 | | OFF | | | | | | | | | | |
| ★ | Reject Ruble 100 | | | ON | | | | | | | | | |
| ★ | Accept Ruble 100 | | | OFF | | | | | | | | | |
| ★ | Reject Ruble 500 | | | | ON | | | | | | | | |
| ★ | Accept Ruble 500 | | | | OFF | | | | | | | | |
| ★ | Reject Ruble 1000 | | | | | ON | | | | | | | |
| ★ | Accept Ruble 1000 | | | | | OFF | | | | | | | |
| ★ | Reserved | | | | | | ON | | | | | | |
| ★ | Reserved | | | | | | OFF | | | | | | |
| ★ | Harness Disable | | | | | | | ON | | | | | |
| ★ | Harness Enable | | | | | | | OFF | | | | | |
| ★ | Inhibit Active High | | | | | | | | ON | | | | |
| ★ | Inhibit Active Low | | | | | | | | OFF | | | | |
| ★ | 1 pulse / Ruble 10 | | | | | | | | | OFF | OFF | | |
| ★ | 2 pulse / Ruble 10 | | | | | | | | | ON | OFF | | |
| ★ | 5 pulse / Ruble 10 | | | | | | | | | OFF | ON | | |
| ★ | 20 pulse / Ruble 10 | | | | | | | | | ON | ON | | |
| ★ | Pulse Speed | 50ms on / 50ms off | | | | | | | | | | OFF | OFF |
| | | 60ms on / 300ms off | | | | | | | | | | ON | OFF |
| | | 30ms on / 50ms off | | | | | | | | | | OFF | ON |
| | | 150ms on / 150ms off | | | | | | | | | | ON | ON |

★ Manufacture setting

◆ Note : (1) Reset the bill acceptor after setting the dip switch.

(2) SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

V7E/LX7-RUR5

DIP SWITCHES SETTING : 2(Pulse)

| | FUNCTION | SW1 | SW2 | SW3 | SW4 |
|---|-------------------|-----|-----|-----|-----|
| ★ | Pulse Normal High | ON | | | |
| | Pulse Normal Low | OFF | | | |
| | ICT Interface | | OFF | ON | |
| ★ | Pulse Mode | | ON | OFF | |
| | M.D.B Interface | | ON | ON | |
| ★ | Reserved | | | | ON |
| | | | | | OFF |

Currency Assign Data

| Interface Bill value | ICT | Pulse | MDB |
|----------------------|------------|------------|------------|
| BV1 | Ruble 10 | Ruble 10 | Ruble 10 |
| BV2 | Ruble 50 | Ruble 50 | Ruble 50 |
| BV3 | Ruble 100 | Ruble 100 | Ruble 100 |
| BV4 | Ruble 500 | Ruble 500 | Ruble 500 |
| BV5 | Ruble 1000 | Ruble 1000 | Ruble 1000 |

DIP SWITCHES SETTING : 3(ICT)

| | FUNCTION | SW1 | SW2 | SW3 | SW4 |
|---|-----------------|-----|-----|-----|-----|
| ★ | Reserved | ON | | | |
| | | OFF | | | |
| ★ | ICT Interface | | OFF | ON | |
| | Pulse Mode | | ON | OFF | |
| | M.D.B Interface | | ON | ON | |
| ★ | Reserved | | | | ON |
| | | | | | OFF |

DIP SWITCHES SETTING : 3(M.D.B)

| | FUNCTION | SW1 | SW2 | SW3 | SW4 |
|---|---|-----|-----|-----|-----|
| ★ | Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2 | ON | | | |
| | | OFF | | | |
| | Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0 | | | | |
| | Pulse Mode | | ON | OFF | |
| ★ | M.D.B Interface | | ON | ON | |
| | ICT Interface | | OFF | ON | |
| ★ | Reserved | | | | ON |
| | | | | | OFF |

★ Manufacture setting

◆ Remove the front cover and the dip-switch is on the CPU board.