

V7E/LX7-TWD4

V7E/LX7 Option Switch Settings: 1(Pulse/ICT/MDB)

Supported bill TWD 100, 200, 500, 1000 4bills.

V7E/LX7 dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject TWD 100	ON											
★ Accept TWD 100	OFF											
★ Reject TWD 200		ON										
★ Accept TWD 200		OFF										
★ Reject TWD 500			ON									
★ Accept TWD 500			OFF									
★ Reject TWD 1000				ON								
★ Accept TWD 1000				OFF								
★ Reserved				ON								
★ Reserved				OFF								
★ Reserved					ON							
★ Reserved					OFF							
★ Harness Disable						ON						
★ Harness Enable						OFF						
★ Inhibit Active High							ON					
★ Inhibit Active Low							OFF					
★ 1 pulse / TWD 100								OFF	OFF			
2 pulses / TWD 100								ON	OFF			
10 pulses / TWD 100								OFF	ON			
20 pulses / TWD 100								ON	ON			
★ Pulse Speed	50ms on / 50ms off									OFF	OFF	
	60ms on / 300ms off									ON	OFF	
	30ms on / 50ms off									OFF	ON	
	150ms on / 150ms off									ON	ON	

★ Manufacture setting

Note : (1) Please reset the bill acceptor after any changes on Dip switch.

(2) SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

V7E/LX7-TWD4(Pulse/ICT/MDB)

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
★ Pulse Mode		ON	OFF	
ICT Interface		OFF	ON	
MDB Interface		ON	ON	
Reserved		OFF	OFF	
★ Reserved				ON
				OFF

Currency Assign Data

Interface Bill value	ICT	Pulse	MDB
BV1	TWD 100	TWD 100	TWD 100
BV2	TWD 200	TWD 200	TWD 200
BV3	TWD 500	TWD 500	TWD 500
BV4	TWD 1000	TWD 1000	TWD 1000

DIP SWITCHES SETTING : 2(ICT)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
★ ICT Interface		OFF	ON	
MDB Interface		ON	ON	
Reserved		OFF	OFF	
★ Reserved				ON
				OFF

DIP SWITCHES SETTING : 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
Pulse Mode		ON	OFF	
★ ICT Interface		OFF	ON	
MDB Interface		ON	ON	
Reserved		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

Note 1: Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.

2: Remove the front cover and the dip-switch in on the CPU board.