

# BR2300-CZK4

## BR2300 DIP SWITCHES SETTING : (MDB/ICT-BC/ccTalk)

Supported bill CZK 100, 200, 500, 1000 4 bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	Reject CZK 100 & 200	ON									
	Accept CZK 100 & 200	OFF									
	Reject CZK 500		ON								
★	Accept CZK 500		OFF								
	Reject CZK 1000			ON							
★	Accept CZK 1000			OFF							
	High Acceptance (Note.3)				ON						
★	High Security				OFF						
★	Scaling Factor (SF)=100 Decimal Point Position(DPP)=2	(MDB only)				ON					
	Scaling Factor (SF)=1 Decimal Point Position(DPP)=0					OFF					
★	Normal						OFF	OFF			
	Load Banknote to Recycle						ON	OFF			
	Load Banknote to Stacker						OFF	ON			
	Unload Banknote to Stacker						ON	ON			
★	ccTalk								ON	OFF	
	ccTalk (Note.1)								OFF	ON	
★	MDB Mode								OFF	OFF	
★	ICT-BC Mode								ON	ON	
	ccTalk	MDB Mode			ICT-BC Mode						
★	Encryption MODE	★ Virtual MDB Recycler Function (Note.2)			Connect with MDB Connector						ON
	Decrypt MODE	Standard MDB Recycler Function			★ Connect with RS232 Connector						OFF

### ★ Manufacture setting

After setting dip switch of the credit pulses, you should reset the bill acceptor again.

Note.1: Turn this dip to with restart the bill acceptor will restore ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

Note.2: Recycled Banknote represents virtual MDB coin type.

Note.3: Calibration card is needed.

### Currency Assign Data

Interface Bill value	ccTalk	ICT-BC	MDB
BV1	CZK 100	CZK 100	CZK 100
BV2	CZK 200	CZK 200	CZK 200
BV3	CZK 500	CZK 500	CZK 500
BV4	CZK 1000	CZK 1000	CZK 1000

Recycler banknote inventory	
CZK 100	45 pcs
CZK 200	45 pcs
CZK 500	40 pcs
CZK 1000	40 pcs