

BR2300-MYR6

BR2300 DIP SWITCHES SETTING : (MDB/ICT-BC/ccTalk)

Supported bill MYR 1, 5, 10, 20, 50, 100 6 bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	Reject MYR 1 & 5 & 10	ON									
	Accept MYR 1 & 5 & 10	OFF									
★	Reject MYR 20		ON								
	Accept MYR 20		OFF								
★	Reject MYR 50 & 100			ON							
	Accept MYR 50 & 100			OFF							
★	High Acceptance (Note.3)			ON							
	High Security			OFF							
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	(MDB only)				ON					
★	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0					OFF					
★	Normal						OFF	OFF			
	Load Banknote to Recycle						ON	OFF			
	Load Banknote to Stacker						OFF	ON			
	Unload Banknote to Stacker						ON	ON			
★	ccTalk								ON	OFF	
	ccTalk (Note.1)								OFF	ON	
★	MDB Mode								OFF	OFF	
★	ICT-BC Mode								ON	ON	
	ccTalk	MDB Mode				ICT-BC Mode					
★	Encryption MODE	Virtual MDB Recycler Function (Note.2)				Connect with MDB Connector				ON	
	Decrypt MODE	Standard MDB Recycler Function				Connect with RS232 Connector				OFF	

★ Manufacture setting

After setting dip switch of the credit pulses, you should reset the bill acceptor again.

Note.1: Turn this dip to with restart the bill acceptor will restore ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

Note.2: Recycled Banknote represents virtual MDB coin type.

Note.3: High acceptance mode will increasing accepting rate, however, it will reduce the security level of Bill Acceptor

Note.4: calibrate card.

Currency Assign Data

Interface Bill value	ccTALK	ICT-BC	MDB
BV1	MYR 1	MYR 1	MYR 1
BV2			
BV3	MYR 5	MYR 5	MYR 5
BV4	MYR 10	MYR 10	MYR 10
BV5	MYR 50	MYR 50	MYR 50
BV6	MYR 100	MYR 100	MYR 100
BV7	MYR 20	MYR 20	MYR 20