



CHF4

L77&L77F-P3/P6 DIP SWITCHES SETTING : 1(Pulse/ICT/MDB)

Supported bill Sw F 10, 20, 50, 100

4bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / Sw F 10	OFF	OFF	OFF							
	2 Pulse / Sw F 10	OFF	OFF	ON							
	3 Pulse / Sw F 10	OFF	ON	OFF							
	4 Pulse / Sw F 10	OFF	ON	ON							
	5 Pulse / Sw F 10	ON	OFF	OFF							
	10 Pulse / Sw F 10	ON	OFF	ON							
	20 Pulse / Sw F 10	ON	ON	OFF							
	100 Pulse / Sw F 10	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low					ON					
★	Inhibit level Active High					OFF					
★	Accept Sw F 10						ON				
	Reject Sw F 10						OFF				
★	Accept Sw F 20							ON			
	Reject Sw F 20							OFF			
★	Accept Sw F 50								ON		
	Reject Sw F 50								OFF		
★	Accept Sw F 100									ON	
	Reject Sw F 100									OFF	
★	Reserve										ON
	Reserve										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

(3) BV1=10, BV2=20, BV3=50, BV4=100.

L77&L77F-CHF4(Pulse/ICT/MDB)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Mode		ON	OFF	
	ICT Interface		OFF	ON	
	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON	OFF	
★	ICT Interface		OFF	ON	
	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100	ON			
	Decimal Point Position (DPP) = 2				
	Scaling Factor (SF) = 1	OFF			
	Decimal Point Position (DPP) = 0				
	Pulse Mode		ON	OFF	
	ICT Interface		OFF	ON	
★	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting