

GEL6

L77&L77F DIP SWITCHES SETTING : 1(Pulse/RS232 A0/RS232 B0)

Supported bill Lari 5, 10, 20, 50, 100, 200 6bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / Lari 5	OFF	OFF	OFF							
	2 Pulse / Lari 5	OFF	OFF	ON							
	3 Pulse / Lari 5	OFF	ON	OFF							
	4 Pulse / Lari 5	OFF	ON	ON							
	5 Pulse / Lari 5	ON	OFF	OFF							
	10 Pulse / Lari 5	ON	OFF	ON							
	20 Pulse / Lari 5	ON	ON	OFF							
	100 Pulse / Lari 5	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low					ON					
★	Inhibit level Active High					OFF					
★	Accept Lari 5						ON				
	Reject Lari 5						OFF				
★	Accept Lari 10							ON			
	Reject Lari 10							OFF			
★	Accept Lari 20								ON		
	Reject Lari 20								OFF		
★	Accept Lari 50									ON	
	Reject Lari 50									OFF	
★	Accept Lari 100 & 200										ON
	Reject Lari 100 & 200										OFF

★ Manufacture setting

Note:(1) Please reset the bill acceptor after any changes on Dip switch.

(2) Dip switches 1 to 5 are only for Pulse model.

Currency Assign Data

Interface Bill value	RS232 A0	Pulse	RS232 B0
BV1	Lari 5	Lari 5	Lari 5
BV2	Lari 10	Lari 10	Lari 10
BV3	Lari 20	Lari 20	Lari 20
BV4	Lari 50	Lari 50	Lari 50

Interface Bill value	RS232 A0	Pulse	RS232 B0
BV5	Lari 100	Lari 100	Lari 100
BV6	Lari 200	Lari 200	Lari 200

L77&L77F-GEL6(Pulse/RS232 A0/RS232 B0)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Mode		ON	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(RS232 A0)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON	OFF	
	RS232 B0 Interface		OFF	OFF	
★	RS232 A0 Mode		ON	ON	
	Reserved				ON
					OFF

Note:

ESCROW DATA	
Code	Denomination
61h	Reserved
62h	Reserved
63h	Lari 5
64h	Lari 10
65h	Lari 20
66h	Lari 50
67h	Lari 100
68h	Lari 200
69h	Reserved

CURRENCY ASSIGN DATA			
Code	Country	Denomination	EXP
61h	76h	00h	00h
62h	76h	00h	00h
63h	76h	05h	00h
64h	76h	0Ah	00h
65h	76h	14h	00h
66h	76h	32h	00h
67h	76h	64h	00h
68h	76h	C8h	00h
69h	00h	00h	00h

★ Manufacture setting

DIP SWITCHES SETTING : 2(RS232 B0)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
★	RS232 B0 Mode		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting