

L77&L77F-KHR9

L77-P3/P6 L77F-P2/P5 DIP SWITCHES SETTING : 1(Pulse/ICT/MDB)

Supported bill KHR 100, 500, 1000, 2000, 5000, 10000, 20000, 50000, 100000 9bills.

With stacker : 100, 500, 1000, 2000, 5000, 10000, 20000, 50000

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / KHR 100 (Note.3) KHR 500 (Note.4)	OFF	OFF	OFF							
2 Pulse / KHR 100 (Note.3) KHR 500 (Note.4)	OFF	OFF	ON							
3 Pulse / KHR 100 (Note.3) KHR 500 (Note.4)	OFF	ON	OFF							
4 Pulse / KHR 100 (Note.3) KHR 500 (Note.4)	OFF	ON	ON							
5 Pulse / KHR 100 (Note.3) KHR 500 (Note.4)	ON	OFF	OFF							
10 Pulse / KHR 100 (Note.3) KHR 500 (Note.4)	ON	OFF	ON							
20 Pulse / KHR 100 (Note.3) KHR 500 (Note.4)	ON	ON	OFF							
100 Pulse / KHR 100 (Note.3) KHR 500 (Note.4)	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low				ON						
★ Inhibit level Active High				OFF						
★ Accept KHR 100				ON						
Reject KHR 100				OFF						
★ Accept KHR 500 & 1000				ON						
Reject KHR 500 & 1000				OFF						
★ Accept KHR 2000 & 5000				ON						
Reject KHR 2000 & 5000				OFF						
★ Accept KHR 10000 & 20000				ON						
Reject KHR 10000 & 20000				OFF						
★ Accept KHR 50000 & 100000				ON						
Reject KHR 50000 & 100000				OFF						

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

(3) Dip 6 turn ON (MDB Protocol : Reject KHR 50000 & KHR 100000).

(4) Dip 6 turn OFF (MDB Protocol : Accept KHR 50000 & KHR 100000).

L77-KHR9 P3/P6 L77F-KHR9 P2/P5 (Pulse/ICT/MDB)

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
★ Pulse Mode		ON	OFF	
ICT Interface		OFF	ON	
MDB Mode		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
★ ICT Interface		OFF	ON	
MDB Mode		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
Pulse Mode		ON	OFF	
ICT Interface		OFF	ON	
★ MDB Mode		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

Currency Assign Data

Dip 6 ON				
Interface Bill value	ICT	Pulse	MDB	
BV1	KHR 100	KHR 100	KHR 100	
BV2	KHR 500	KHR 500	KHR 500	
BV3	KHR 1000	KHR 1000	KHR 1000	
BV4	KHR 2000	KHR 2000	KHR 2000	
BV5	KHR 5000	KHR 5000	KHR 5000	
BV6	KHR 10000	KHR 10000	KHR 10000	
BV7	KHR 20000	KHR 20000	KHR 20000	
BV8	KHR 50000	KHR 50000		
BV9	KHR 100000	KHR 100000		

Currency Assign Data

Dip 6 OFF				
Interface Bill value	ICT	Pulse	MDB	
BV1	KHR 500	KHR 500	KHR 500	
BV2	KHR 1000	KHR 1000	KHR 1000	
BV3	KHR 2000	KHR 2000	KHR 2000	
BV4	KHR 5000	KHR 5000	KHR 5000	
BV5	KHR 10000	KHR 10000	KHR 10000	
BV6	KHR 20000	KHR 20000	KHR 20000	
BV7	KHR 50000	KHR 50000	KHR 50000	
BV8	KHR 100000	KHR 100000	KHR 100000	