

PLN5

L77&L77F DIP SWITCHES SETTING : 1(Pulse/RS232 A0/RS232 B1)

Supported bill PLN 10, 20, 50, 100, 200 5bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / PLN 10	OFF	OFF	OFF							
	2 Pulse / PLN 10	OFF	OFF	ON							
	3 Pulse / PLN 10	OFF	ON	OFF							
	4 Pulse / PLN 10	OFF	ON	ON							
	5 Pulse / PLN 10	ON	OFF	OFF							
	10 Pulse / PLN 10	ON	OFF	ON							
	20 Pulse / PLN 10	ON	ON	OFF							
	100 Pulse / PLN 10	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low					ON					
★	Inhibit level Active High					OFF					
★	Accept PLN 10						ON				
	Reject PLN 10						OFF				
★	Accept PLN 20							ON			
	Reject PLN 20							OFF			
★	Accept PLN 50								ON		
	Reject PLN 50								OFF		
★	Accept PLN 100									ON	
	Reject PLN 100									OFF	
★	Accept PLN 200										ON
	Reject PLN 200										OFF

★ Manufacture setting

Note:(1) Please reset the bill acceptor after any changes on Dip switch.

(2) Dip switch 1 to 5 are only for Pulse mode.

(3) Turn this dip to with restart the bill acceptor will restore ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

L77&L77F-PLN5(Pulse/RS232 A0/RS232 B1)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Mode		ON	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(RS232 B1)

	FUNCTION	SW1	SW2	SW3	SW4
	8-bit checksum	ON			
★	CRC 16-bit checksum	OFF			
★	RS232 B1 Interface		OFF	OFF	
	RS232 B1 Parameters Restore Switch Please see "Note" for detail		OFF	ON	
★	Encryption Mode				ON
	Decrypt Mode				OFF

★ Manufacture setting

Note: 1 · Put this switch to on and reset power will restore the ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

2 · L77 optional.

DIP SWITCHES SETTING : 2(RS232 A0)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
★	RS232 A0 Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	RS232 A0	RS232 B1
BV1	PLN 10	PLN 10	PLN 10
BV2	PLN 20	PLN 20	PLN 20
BV3	PLN 50	PLN 50	PLN 50
BV4	PLN 100	PLN 100	PLN 100
BV5	PLN 200	PLN 200	PLN 200