

L77F/PL77-UAH10

L77F/PL77 Option Switch Settings : 1(Pulse/RS232 A0/ccNet/ICT104U)

Supported bill HRYVEN 1, 2, 5, 10, 20, 50, 100, 200, 500, 1000 10bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / HRYVEN 1 & 5 (Note.3)	OFF	OFF	OFF							
2 Pulses / HRYVEN 1 & 5 (Note.3)	OFF	OFF	ON							
3 Pulses / HRYVEN 1 & 5 (Note.3)	OFF	ON	OFF							
4 Pulses / HRYVEN 1 & 5 (Note.3)	OFF	ON	ON							
5 Pulses / HRYVEN 1 & 5 (Note.3)	ON	OFF	OFF							
10 Pulses / HRYVEN 1 & 5 (Note.3)	ON	OFF	ON							
20 Pulses / HRYVEN 1 & 5 (Note.3)	ON	ON	OFF							
100 Pulses / HRYVEN 1 & 5 (Note.3)	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept HRYVEN 1 & 2 (Note.3)						ON				
Reject HRYVEN 1 & 2 (Note.3)						OFF				
★ Accept HRYVEN 5 & 10 & 20 & 50							ON			
Reject HRYVEN 5 & 10 & 20 & 50							OFF			
★ Accept HRYVEN 100 & 200								ON		
Reject HRYVEN 100 & 200								OFF		
★ Accept HRYVEN 500 & 1000									ON	
Reject HRYVEN 500 & 1000									OFF	
Simulation BillBox Has Been Removed										ON
★ Default										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

(3) Pulse Mode:

Dip 6 turn ON, One Pulse per HRYVEN 1.

Dip 6 turn OFF, One Pulse per HRYVEN 5.

Currency Assign Data

Interface	Pulse		RS232 A0	ccNet	ICT104U
	Bill value	Dip 6 is ON Dip 6 is OFF			
BV1	1	5	1	1	1
BV2	2	10	2	2	2
BV3	5	20	5	5	5
BV4	10	50	10	10	10
BV5	20	100	20	20	20
BV6	50	200	50	50	50
BV7	100	500	100	100	100
BV8	200		200	200	200
BV9	500		500	500	500
BV10	1000		1000	1000	1000

L77F/PL77-UAH10(Pulse/RS232 A0/ccNet/ICT104U)

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal High	ON			
Credit-Pulse Normal Low	OFF			
RS232 A0 Mode		ON	ON	
★ Pulse Mode		ON	OFF	
ccNet Mode		OFF	OFF	
ICT104U Mode		OFF	ON	
Reserved				ON
★				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(RS232 A0)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
OFF				
★ RS232 A0 Mode		ON	ON	
Pulse Mode		ON	OFF	
ccNet Mode		OFF	OFF	
ICT104U Mode		OFF	ON	
Reserved				ON
★				OFF

★ Manufacture setting

RS232 A0 INFORMATION

BillType Data		
Code	Denomination	
1	HRIVEN 1	
2	HRIVEN 2	
3	HRIVEN 5	
4	HRIVEN 10	
5	HRIVEN 20	
6	HRIVEN 50	
7	HRIVEN 100	
8	HRIVEN 200	
9	HRIVEN 500	
10	HRIVEN1000	

DIP SWITCHES SETTING : 2(ccNet)

FUNCTION	SW1	SW2	SW3	SW4
Baud rate 19200	ON			
★ Baud rate 9600	OFF			
RS232 A0 Mode		ON	ON	
Pulse Mode		ON	OFF	
★ ccNet Mode		OFF	OFF	
ICT104U Mode		OFF	ON	
Reserved				ON
★				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104U)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
RS232 A0 Mode		ON	ON	
Pulse Mode		ON	OFF	
ccNet Mode		OFF	OFF	
★ ICT104U Mode		OFF	ON	
Reserved				ON
★				OFF

★ Manufacture setting