

## L77F/PL77/L77T-THB5

### L77T DIP SWITCHES SETTING : 1(Pulse/RS232 A0/V2.2)

Supported bill THB 20, 50, 100, 500, 1000 5bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / THB 10	OFF	OFF	OFF							
2 Pulses / THB 10	OFF	OFF	ON							
3 Pulses / THB 10	OFF	ON	OFF							
4 Pulses / THB 10	OFF	ON	ON							
5 Pulses / THB 10	ON	OFF	OFF							
10 Pulses / THB 10	ON	OFF	ON							
20 Pulses / THB 10	ON	ON	OFF							
100 Pulses / THB 10	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low				ON						
★ Inhibit level Active High				OFF						
★ Accept THB 20 & 50				ON						
Reject THB 20 & 50				OFF						
★ Accept THB 100				ON						
Reject THB 100				OFF						
★ Accept THB 500				ON						
Reject THB 500				OFF						
★ Accept THB 1000				ON						
Reject THB 1000				OFF						
★ High Security				ON						
High Acceptance (Nota.3)				OFF						

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

(3) High acceptance mode will increasing accepting rate, however, it will reduce the security level of Bill Acceptor.

### Currency Assign Data

Interface Bill value	Pulse	RS232 A0	V2.2
BV1	20	20	20
BV2	50	50	50
BV3	100	100	100
BV4	500	500	500
BV5	1000	1000	1000

## L77F/PL77/L77T-THB5(Pulse/RS232 A0/V2.2)

### DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
★ Pulse Mode		ON	OFF	
RS232 A0 Mode		ON	ON	
V2.2 Mode		OFF	ON	
Reserved		OFF	OFF	
Power On Motor Plus				ON
★ Power On Motor Minus				OFF

★ Manufacture setting

### DIP SWITCHES SETTING : 2(RS232 A0)

FUNCTION		SW1	SW2	SW3	SW4	RS232 A0 INFORMATION		
★	Reserved	ON				BIType Data		
		OFF				Code	Denomination	
Pulse Mode		ON	OFF	1		Reserved		
★	RS232 A0 Mode		ON	ON		2	THB 20	
	V2.2 Mode		OFF	ON		3	THB 50	
	Reserved		OFF	OFF		4	THB 100	
	Power On Motor Plus					ON	5	Reserved
★	Power On Motor Minus					OFF	6	THB 500
						7	THB 1000	
						8	Reserved	
						9	Reserved	

★ Manufacture setting

★ Manufacture setting

### DIP SWITCHES SETTING : 2(V2.2)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
RS232 A0 Mode		ON	ON	
★ V2.2 Mode		OFF	ON	
Reserved		OFF	OFF	
Power On Motor Plus				ON
★ Power On Motor Minus				OFF

★ Manufacture setting