

L83-BGN5

L83 Option Switch Settings : 1(Pulse/RS232 A0/ccNet/ICT)

Supported bill BGN 5, 10, 20, 50, 100 5bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / BGN 5	OFF	OFF	OFF							
	2 Pulses / BGN 5	OFF	OFF	ON							
	3 Pulses / BGN 5	OFF	ON	OFF							
	4 Pulses / BGN 5	OFF	ON	ON							
	5 Pulses / BGN 5	ON	OFF	OFF							
	10 Pulses / BGN 5	ON	OFF	ON							
	20 Pulses / BGN 5	ON	ON	OFF							
	100 Pulses / BGN 5	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept BGN 5					ON					
	Reject BGN 5					OFF					
★	Accept BGN 10						ON				
	Reject BGN 10						OFF				
★	Accept BGN 20							ON			
	Reject BGN 20							OFF			
★	Accept BGN 50 & 100								ON		
	Reject BGN 50 & 100								OFF		
	Simulation BillBox Has Been Removed									ON	
★	Default										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

Currency Assign Data

Interface Bill value	Pulse	RS232 A0	ccNet	ICT104U
BV1	BGN 5	BGN 5	BGN 5	BGN 5
BV2	BGN 10	BGN 10	BGN 10	BGN 10
BV3	BGN 20	BGN 20	BGN 20	BGN 20
BV4	BGN 50	BGN 50	BGN 50	BGN 50
BV5	BGN 100	BGN 100	BGN 100	BGN 100

L83-BGN5(Pulse/RS232 A0/ccNet/ICT)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(RS232 A0)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
★	RS232 A0 Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

RS232 A0 INFORMATION	
BillType Data	
Code	Denomination
1	Reserved
2	Reserved
3	BGN 5
4	BGN 10
5	BGN 20
6	BGN 50
7	BGN 100

DIP SWITCHES SETTING : 2(ccNet)

	FUNCTION	SW1	SW2	SW3	SW4
	Baud rate 19200	ON			
★	Baud rate 9600	OFF			
★	ccNet Mode		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
★	ICT104U Mode		OFF	ON	
★	Reserved				ON
					OFF

★ Manufacture setting