

L83-CHF4

L83/P3/P6 DIP SWITCHES SETTING : 1(Pulse/RS232 A0)

Supported bill CHF 10, 20, 50, 100 4bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / CHF 10	OFF	OFF	OFF							
	2 Pulses / CHF 10	OFF	OFF	ON							
	3 Pulses / CHF 10	OFF	ON	OFF							
	4 Pulses / CHF 10	OFF	ON	ON							
	5 Pulses / CHF 10	ON	OFF	OFF							
	10 Pulses / CHF 10	ON	OFF	ON							
	20 Pulses / CHF 10	ON	ON	OFF							
	100 Pulses / CHF 10	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept CHF 10				ON						
	Reject CHF 10				OFF						
★	Accept CHF 20										
	Reject CHF 20										
★	Accept CHF 50										
	Reject CHF 50										
★	Accept CHF 100										
	Reject CHF 100										
★	Reserve										
	Reserve										
	Reserve										

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

(3) High acceptance mode will increasing accepting rate, however, it will reduce the security level of Bill Acceptor.

Appendix

L83-CHF4(Pulse/RS232 A0)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal High	ON			
	Credit-Pulse Normal Low	OFF			
★	Pulse Mode		ON		
	RS232 A0 Interface Mode		OFF		
★	Reserved				
★					ON
★					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(RS232 A0)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
★	Pulse Mode		ON		
★	RS232 A0 Interface Mode		OFF		
★	Reserved			ON	
				OFF	
★					ON
★					OFF

★ Manufacture setting

RS232 A0 INFORMATION

BillType Data	
Code	Denomination
1	Reserved
2	Reserved
3	Reserved
4	CHF 10
5	CHF 20
6	CHF 50
7	CHF 100
8	Reserved

Currency Assign Data

Interface Bill value	RS232 A0	Pulse
BV1	CHF 10	CHF 10
BV2	CHF 20	CHF 20
BV3	CHF 50	CHF 50
BV4	CHF 100	CHF 100