

L83-INR7

L83 Option Switch Settings : 1(Pulse/RS232 A0/ccTalk/Parallel A5)

Supported bill INR 10, 20, 50, 100, 200, 500, 2000 7bills.
With stacker : 10, 20, 50, 100, 200, 500 6bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / INR 10	OFF	OFF	OFF							
	2 Pulses / INR 10	OFF	OFF	ON							
	3 Pulses / INR 10	OFF	ON	OFF							
	4 Pulses / INR 10	OFF	ON	ON							
	5 Pulses / INR 10	ON	OFF	OFF							
	10 Pulses / INR 10	ON	OFF	ON							
	20 Pulses / INR 10	ON	ON	OFF							
	100 Pulses / INR 10	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept INR 10 & 20 & 50					ON					
	Reject INR 10 & 20 & 50					OFF					
★	Accept INR 100						ON				
	Reject INR 100						OFF				
★	Accept INR 200							ON			
	Reject INR 200							OFF			
★	Accept INR 500								ON		
	Reject INR 500								OFF		
★	Accept INR 2000									ON	
	Reject INR 2000									OFF	

★ Manufacture setting

Note.1 Please reset the bill acceptor after any changes on Dip switch.

Note.2 Dip Switch 1 to 5 are only for Pulse mode.

Note.3 Turn this dip to with restart the bill acceptor will restore ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

Currency Assign Data

Interface Bill value	Pulse	RS232 A0	ccTalk	Parallel A5
BV1	INR 10	INR 10	INR 10	INR 10
BV2	INR 20	INR 20	INR 20	INR 20
BV3	INR 50	INR 50	INR 50	INR 50
BV4	INR 100	INR 100	INR 100	INR 100
BV5	INR 200	INR 200	INR 200	INR 200
BV6	INR 500	INR 500	INR 500	INR 500
BV7				
BV8	INR 2000	INR 2000	INR 2000	INR 2000

L83-INR7(Pulse/RS232 A0/ccTalk/Parallel A5)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
	RS232 A0 Mode		ON	ON	OFF
★	Pulse Mode		ON	OFF	OFF
	Parallel A5 Mode		ON	OFF	ON

★ Manufacture setting

DIP SWITCHES SETTING : 2(Parallel A5)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	RS232 A0 Mode		ON	ON	OFF
	Pulse Mode		ON	OFF	OFF
★	Parallel A5 Mode		ON	OFF	ON

★ Manufacture setting

DIP SWITCHES SETTING : 2(RS232 A0)

	FUNCTION	SW1	SW2	SW3	SW4
	Reserved	ON			
★	Reserved	OFF			
★	RS232 A0 Mode		ON	ON	OFF
	Pulse Mode		ON	OFF	OFF
	Parallel A5 Mode		ON	OFF	ON

★ Manufacture setting

RS232 A0 INFORMATION

BillType Data	
Code	Denomination
1	INR 10
2	INR 20
3	INR 50
4	INR 100
5	INR 200
6	INR 500
7	Reserved
8	INR 2000
9	Reserved

DIP SWITCHES SETTING : 2(ccTalk)

	FUNCTION	SW1	SW2	SW3	SW4
	8-bit checksum	ON			
★	CRC 16-bit checksum	OFF			
★	ccTalk Mode		OFF	OFF	
	ccTalk Parameters Restore Switch (Please see Note.3 for Detail)		OFF	ON	
★	Encryption Mode				ON
	Decrypt Mode				OFF

★ Manufacture setting

Note.3 Turn this dip to with restart the bill acceptor will restore

ccTalk address to its default value of 40 and the encryption key to its default value of 123456.