

L83-KZT7

L83 DIP SWITCHES SETTING : 1(Pulse/ICT104U/MDB/ccTalk)

Supported bill KZT 200, 500, 1000, 2000, 5000, 10000, 20000 7bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / KZT 100	OFF	OFF	OFF							
2 Pulses / KZT 100	OFF	OFF	ON							
3 Pulses / KZT 100	OFF	ON	OFF							
4 Pulses / KZT 100	OFF	ON	ON							
5 Pulses / KZT 100	ON	OFF	OFF							
10 Pulses / KZT 100	ON	OFF	ON							
20 Pulses / KZT 100	ON	ON	OFF							
100 Pulses / KZT 100	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept KZT 200 & 500						ON				
Reject KZT 200 & 500						OFF				
★ Accept KZT 1000 & 2000							ON			
Reject KZT 1000 & 2000							OFF			
★ Accept KZT 5000 & 10000								ON		
Reject KZT 5000 & 10000								OFF		
★ Accept KZT 20000									ON	
Reject KZT 20000									OFF	
Simulation BillBox Has Been Removed										ON
★ Default										OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ccTalk)

FUNCTION	SW1	SW2	SW3	SW4
8-bit checksum	ON			
★ 16-bit checksum	OFF			
★ ccTalk Interface		OFF	OFF	
ccTalk Parameters Restore Switch (Please see Note.3 for Detail)		OFF	ON	
★ Encryption Mode				ON
Decrypt Mode				OFF

★ Manufacture setting

- Note: (1) Please reset the bill acceptor after set the dip switch.
 (2) Dip switches 1 to 5 are only used for pulse protocol.
 (3) Turn this dip to with restart the bill acceptor will restore ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

L83-KZT7(Pulse/ICT104U/MDB/ccTalk)

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
MDB Mode		ON	ON	OFF
★ Pulse Mode		ON	OFF	OFF
ICT104U Mode		ON	OFF	ON

★ Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
★ MDB Mode		ON	ON	OFF
Pulse Mode		ON	OFF	OFF
ICT104U Mode		ON	OFF	ON

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104U)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
MDB Mode		ON	ON	OFF
Pulse Mode		ON	OFF	OFF
★ ICT104U Mode		ON	OFF	ON

★ Manufacture setting

Currency Assign Data

Interface Bill value	MDB	Pulse	ccTalk	ICT104U
BV1	KZT 200	KZT 200	KZT 200	KZT 200
BV2	KZT 500	KZT 500	KZT 500	KZT 500
BV3	KZT 1000	KZT 1000	KZT 1000	KZT 1000
BV4	KZT 2000	KZT 2000	KZT 2000	KZT 2000
BV5	KZT 5000	KZT 5000	KZT 5000	KZT 5000
BV6	KZT 10000	KZT 10000	KZT 10000	KZT 10000
BV7	KZT 20000	KZT 20000	KZT 20000	KZT 20000