

NK77-KRW4

NK77 DIP SWITCHES SETTING : 1(Pulse/Parallel)

Supported bill ₩ 1000, 5000, 10000, 50000 4bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10	
★	1 Pulse / $\overline{W}$ 1000	OFF	OFF									
	5 Pulse / $\overline{W}$ 1000	ON	OFF									
	10 Pulse / $\overline{W}$ 1000	OFF	ON									
	15 Pulse / $\overline{W}$ 1000	ON	ON									
★	Accept $\overline{W}$ 1000			ON								
	Reject $\overline{W}$ 1000			OFF								
★	Accept $\overline{W}$ 5000				ON							
	Reject $\overline{W}$ 5000				OFF							
★	Accept $\overline{W}$ 10000					ON						
	Reject $\overline{W}$ 10000					OFF						
★	Accept $\overline{W}$ 50000						ON					
	Reject $\overline{W}$ 50000						OFF					
★	Enable Output Sensor Detect							ON				
	Disable Output Sensor Detect							OFF				
★	Fast output Pulse Lo= 50ms Hi=100ms	Parallel 100ms							ON			
	Slow output Pulse Lo=100ms Hi=200ms	Parallel 120ms							OFF			
★	Pulse Mode									ON		
	Parallel Mode									OFF		
★	Reserved										ON	
	Reserved										OFF	

(★) Manufacture setting

Note : Please reset the bill acceptor
after set the dip switch.

Currency Assign Data

Interface Bill value	Pulse	Parallel
BV1	₩ 1000	₩ 1000
BV2	₩ 5000	₩ 5000
BV3	₩ 10000	₩ 10000
BV4	₩ 50000	₩ 50000