

# NK77F-PHP6

## NK77F DIP SWITCHES SETTING : (Pulse/Out of Service/ICT104U)

Supported bill PHP 20, 50, 100, 200, 500, 1000 6bills.

|   | FUNCTION                       | SW1 | SW2 | SW3 | SW4 | SW5 | SW6 | SW7 | SW8 | SW9 | SW10 |
|---|--------------------------------|-----|-----|-----|-----|-----|-----|-----|-----|-----|------|
| ★ | 1 Pulse / PHP 10               | OFF | OFF |     |     |     |     |     |     |     |      |
|   | 5 Pulse / PHP 10               | OFF | ON  |     |     |     |     |     |     |     |      |
|   | 10 Pulse / PHP 10              | ON  | OFF |     |     |     |     |     |     |     |      |
|   | 20 Pulse / PHP 10              | ON  | ON  |     |     |     |     |     |     |     |      |
| ★ | Enable Fish Stop               |     |     | ON  |     |     |     |     |     |     |      |
|   | Disable Fish Stop              |     |     | OFF |     |     |     |     |     |     |      |
| ★ | Inhibit level Active Low       |     |     |     | ON  |     |     |     |     |     |      |
|   | Inhibit level Active High      |     |     |     | OFF |     |     |     |     |     |      |
| ★ | Accept PHP 20 & 50 & 100 & 200 |     |     |     |     | ON  |     |     |     |     |      |
|   | Reject PHP 20 & 50 & 100 & 200 |     |     |     |     | OFF |     |     |     |     |      |
| ★ | Accept PHP 500 & 1000          |     |     |     |     |     | ON  |     |     |     |      |
|   | Reject PHP 500 & 1000          |     |     |     |     |     | OFF |     |     |     |      |
|   | Enable Output Sensor Detect    |     |     |     |     |     |     | ON  |     |     |      |
| ★ | Disable Output Sensor Detect   |     |     |     |     |     |     | OFF |     |     |      |
| ★ | Pluse Normal High              |     |     |     |     |     |     |     | ON  |     |      |
|   | Pluse Normal Low               |     |     |     |     |     |     |     | OFF |     |      |
| ★ | Pulse Mode                     |     |     |     |     |     |     |     |     | ON  |      |
|   | ICT104U Mode                   |     |     |     |     |     |     |     |     | OFF |      |
| ★ | Manufacture Default            |     |     |     |     |     |     |     |     |     | ON   |
|   | System Default                 |     |     |     |     |     |     |     |     |     | OFF  |

(★) Manufacture setting

Note:(1) Please reset the bill acceptor after set the dip switch.

(2) Pulse mode has out of service function.

(3) Out of service: Normal High, Error Low.

(4) Pulse speed is LO=50ms/HI=100ms.

## Currency Assign Data

| Interface<br>Bill value | ICT104U  | Pulse    |
|-------------------------|----------|----------|
| BV1                     | PHP 20   | PHP 20   |
| BV2                     | PHP 50   | PHP 50   |
| BV3                     | PHP 100  | PHP 100  |
| BV4                     | PHP 500  | PHP 200  |
| BV5                     | PHP 1000 | PHP 500  |
| BV5                     | PHP 200  | PHP 1000 |