

NK77F-THB5

NK77F DIP SWITCHES SETTING : (ICT10A/ccTalk)

Supported bill THB 20, 50, 100, 500, 1000 5bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	Encryption MODE (Nota.2)	ON									
	Decrypt MODE (Nota.2)	OFF									
	ccTalk Parameters Restore Switch		ON								
★	Please see Note.3 for Detail		OFF								
★	Enable Fish Stop			ON							
	Disable Fish Stop			OFF							
	8-bit checksum				ON						
★	CRC 16-bit checksum				OFF						
★	Accept THB 20 & 50 & 100					ON					
	Reject THB 20 & 50 & 100					OFF					
★	Accept THB 500 & 1000						ON				
	Reject THB 500 & 1000						OFF				
	Enable Output Sensor Detect							ON			
★	Disable Output Sensor Detect							OFF			
★	Reserve								ON		
	Reserve								OFF		
★	ccTalk Mode									ON	
	ICT10A Mode									OFF	
★	Power On Motor Plus										ON
	Power On Motor Minus										OFF

(★) Manufacture setting

Currency Assign Data

Interface Bill value	ccTalk	ICT10A
BV1	THB 20	THB 20
BV2	THB 50	THB 50
BV3	THB 100	THB 100
BV4	THB 500	THB 500
BV5	THB 1000	THB 1000

Note:(1) Please reset the bill acceptor after set the dip switch.

(2) The function is valid when the Dip4 is OFF.

(3) Turn this dip with restart the bill acceptor will restore ccTalk address to its default value of 40 and the encryption key to its default value of 123456.