

XBA mini-USD6

XBA mini Option Switch Settings: 1(Pulse/ICT-BC)

Supported bill USD 1, 5, 10, 20, 50, 100 6bills.

XBA mini dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject USD 1	ON											
★	Accept USD 1	OFF											
★	Reject USD 5		ON										
★	Accept USD 5		OFF										
★	Reject USD 10			ON									
★	Accept USD 10			OFF									
★	Reject USD 20				ON								
★	Accept USD 20				OFF								
★	Reject USD 50 & 100				ON								
★	Accept USD 50 & 100				OFF								
★	Disable Bill Reject 4 Times BA Stop By 30 Sec					ON							
★	Enable Bill Reject 4 Times BA Stop By 30 Sec					OFF							
★	Colorful light							OFF	OFF				
★	The green light flashes							OFF	ON				
	Reserved							ON	OFF				
	No light							ON	ON				
★	Inhibit Active High								ON				
★	Inhibit Active Low								OFF				
	Reserved									ON			
★	Reserved									OFF			
★	Interface Timing Conversion	50ms LO / 50ms HI									OFF	OFF	
		60ms LO / 300ms HI									ON	OFF	
		30ms LO / 50ms HI									OFF	ON	
		150ms LO / 150ms HI									ON	ON	

★ Manufacture setting

Note : (1) After setting dip switch of the credit pulses,you should reset the bill acceptor again.

(2) Calibration card is needed.

(3) ICT BC Protocol supports USB and RS-232

XBA mini-USD6(Pulse/ICT-BC)

Interface Settings: 2(Pulse)

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON		
	Other Mode		OFF		
★	1 pulse / USD 1			OFF	OFF
	2 pulses / USD 1			OFF	ON
	4 pulses / USD 1			ON	OFF
	20 pulses / USD 1			ON	ON

★ Manufacture setting

Interface Settings: 2(ICT-BC)

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
★	Pulse Mode		ON		
★	Other Mode		OFF		
	Reserved			OFF	OFF
	Reserved			OFF	ON
★	ICT-BC Mode			ON	OFF
	Reserved			ON	ON

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	ICT-BC
BV1	1	1
BV2	5	5
BV3	10	10
BV4	20	20
BV5	50	50
BV6	100	100