

## A7/V7-EUR3

### A7/V7 Option Switch Settings:1(Pulse/ccTalk)

Supported bill € 5, 10, 20 3bills.

A7/V7 dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject € 5	ON											
★	Accept € 5	OFF											
★	Reject € 10		ON										
★	Accept € 10		OFF										
★	Reject € 20			ON									
★	Accept € 20			OFF									
★	Reject € 5(2002) & 10(2002)				ON								
★	Accept Normal				OFF								
★	Reject € 20(2002)					ON							
★	Accept Normal					OFF							
★	Reserved						ON						
★	Reserved						OFF						
★	Harness Disable							ON					
★	Harness Enable							OFF					
★	Inhibit Active High								ON				
★	Inhibit Active Low								OFF				
★	1 pulse / € 5									OFF	OFF		
	5 pulse / € 5									ON	OFF		
	10 pulse / € 5									OFF	ON		
	20 pulse / € 5									ON	ON		
★	Pulse Speed	50ms on / 50ms off								OFF		OFF	
		60ms on / 300ms off								ON		OFF	
		30ms on / 50ms off								OFF		ON	
		150ms on / 150ms off								ON		ON	

◆ Factory configuration has all switches in the OFF position.

Note : (1) Reset the bill acceptor after setting the dip switch.

(2) SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

## A7/V7-EUR3(Pulse/ccTalk)

### Interface Settings: 2(Pulse)

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON		
	ccTalk Protocol		OFF		
★	Reserved			ON	
				OFF	
					ON
★					OFF

### Interface Settings: 3(ccTalk)

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON		
★	ccTalk Protocol		OFF		
▲	cctalk Parameters Restore Switch			ON	
	Reserved			OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

▲ Put this switch to on and reset power will restore the cctalk address to its default value of 40,and the encryption key to its default value of 123456. This needs to be done after each White card Calibration.

### Currency Assign Data

Bill value \ Interface	ICT	ccTalk
BV1	€ 5	€ 5
BV2	€ 10	€ 10
BV3	€ 20	€ 20