

L70+/L70F-VND9

L70+/L70F/P5 DIP SWITCHES SETTING : 1(Pulse/ICT104U)

Supported bill VND 1000, 2000, 5000, 10000, 20000, 50000, 100000, 200000, 500000 9bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / VND 1000 / 5000	OFF	OFF	OFF							
2 Pulses / VND 1000 / 5000	OFF	OFF	ON							
3 Pulses / VND 1000 / 5000	OFF	ON	OFF							
4 Pulses / VND 1000 / 5000	OFF	ON	ON							
5 Pulses / VND 1000 / 5000	ON	OFF	OFF							
10 Pulses / VND 1000 / 5000	ON	OFF	ON							
20 Pulses / VND 1000 / 5000	ON	ON	OFF							
100 Pulses / VND 1000 / 5000	ON	ON	ON							
★ Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept VND 1000 & 2000 (Note.3)						ON				
Reject VND 1000 & 2000 (Note.3)						OFF				
★ Accept VND 5000 & 10000							ON			
Reject VND 5000 & 10000							OFF			
★ Accept VND 20000 & 50000								ON		
Reject VND 20000 & 50000								OFF		
★ Accept VND 100000 & 200000									ON	
Reject VND 100000 & 200000									OFF	
★ Accept VND 500000										ON
Reject VND 500000										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

(3) Pulse Mode:

When Dip 6 is OFF, BV1=5000.

When Dip 6 is ON, BV1=1000.

(4) High acceptance mode will increasing accepting rate, however, it will reduce the security level of Bill Acceptor.

L70+/L70F-VND9(Pulse/ICT104U)

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON		
ICT104U Interface		OFF		
High Acceptance (Note.4)			ON	
★ High Security			OFF	
Disable Inverse Mode				ON
★ Enable Inverse Mode				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104U)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON		
★ ICT104U Interface		OFF		
High Acceptance (Note.4)			ON	
★ High Security			OFF	
Disable Inverse Mode				ON
★ Enable Inverse Mode				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	ICT104U	Pulse	
		When Dip 6 is ON	When Dip 6 is OFF
BV1	VND 1000	VND 1000	VND 5000
BV2	VND 2000	VND 2000	VND 10000
BV3	VND 5000	VND 5000	VND 20000
BV4	VND 10000	VND 10000	VND 50000
BV5	VND 20000	VND 20000	VND 100000
BV6	VND 50000	VND 50000	VND 200000
BV7	VND 100000	VND 100000	VND 500000
BV8	VND 200000	VND 200000	
BV9	VND 500000	VND 500000	