

V7E+/LX7-BGN2

V7E+/LX7 Option Switch Settings: 1(Pulse/ICT104U/RS232 A0/ccNet)

Supported bill BGN 5, 10 2 bills.

V7E+/LX7 dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject BGN 5	ON											
★	Accept BGN 5	OFF											
★	Reject BGN 10		ON										
★	Accept BGN 10		OFF										
	Reserved			ON									
★	Reserved			OFF									
	Reserved				ON								
★	Reserved			OFF									
★	Reserved				ON								
★	Reserved				OFF								
	Reserved					ON							
★	Reserved				OFF								
	Pulse Mode												
	Other Mode												
★	Harness Disable		BA stops working when fishing				ON						
★	Harness Enable		Normal				OFF						
★	Inhibit Active High							ON					
★	Inhibit Active Low							OFF					
★	1 pulse / BGN 1								OFF	OFF			
★	2 pulses / BGN 1								ON	OFF			
★	4 pulses / BGN 1								OFF	ON			
★	20 pulses / BGN 1								ON	ON			
★	Pulse Speed		50ms LO / 50ms HI								OFF	OFF	
			60ms LO / 300ms HI								ON	OFF	
			30ms LO / 50ms HI								OFF	ON	
			150ms LO / 150ms HI								ON	ON	

★ Manufacture setting

Note : (1) Default setting.

(2) Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.

(3) Remove the front cover and the dip-switch in on the CPU board.

V7E+/LX7-BGN2(Pulse/ICT104U/RS232 A0/ccNet)

DIP SWITCHES SETTING: 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Mode		ON	OFF	
	ICT104U Mode		OFF	OFF	
	ccNet Mode		ON	ON	
	RS232 A0 Mode		OFF	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

DIP SWITCHES SETTING: 2(ICT104U)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
★	Pulse Mode		ON	OFF	
★	ICT104U Mode		OFF	OFF	
	ccNet Mode		ON	ON	
	RS232 A0 Mode		OFF	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

DIP SWITCHES SETTING: 2(ccNet)

	FUNCTION	SW1	SW2	SW3	SW4
	19200 Baud rate	ON			
★	9600 Baud rate	OFF			
	Pulse Mode		ON	OFF	
	ICT104U Mode		OFF	OFF	
★	ccNet Mode		ON	ON	
	RS232 A0 Mode		OFF	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	RS232 A0	ccNet	ICT104U
BV1	BGN 5	BGN 5	BGN 5	BGN 5
BV2	BGN 10	BGN 10	BGN 10	BGN 10

DIP SWITCHES SETTING: 2(RS232 A0)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON	OFF	
	ICT104U Mode		OFF	OFF	
★	ccNet Mode		ON	ON	
★	RS232 A0 Mode		OFF	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

RS232 A0 INFORMATION

BillType Data	
Code	Denomination
1	Reserved
2	Reserved
3	BGN 5
4	BGN 10
5	Reserved
6	Reserved
7	Reserved
8	Reserved