

V7E/LX7-CAD5

V7E/LX7 Option Switch Settings: 1(Pulse/ICT104U/MDB/RS232 A0)

Supported bill CAD 5, 10, 20, 50, 100 5 bills.

V7E/LX7 dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject CAD 5	ON											
★ Accept CAD 5	OFF											
★ Reject CAD 10		ON										
★ Accept CAD 10		OFF										
★ Reject CAD 20			ON									
★ Accept CAD 20			OFF									
★ Reject CAD 50				ON								
★ Accept CAD 50				OFF								
★ Reject CAD 100					ON							
★ Accept CAD 100					OFF							
★ Reserved						ON						
★ Reserved						OFF						
★ Pulse Mode	Other Mode											
★ Harness Disable	BA stops working when fishing						ON					
★ Harness Enable	Normal						OFF					
★ Inhibit Active High							ON					
★ Inhibit Active Low							OFF					
★ 1 pulse / CAD 5								OFF	OFF			
★ 2 pulses / CAD 5								ON	OFF			
★ 4 pulses / CAD 5								OFF	ON			
★ 20 pulses / CAD 5								ON	ON			
★ Pulse Speed	50ms LO / 50ms HI								OFF	OFF		
	60ms LO / 300ms HI								ON	OFF		
	30ms LO / 50ms HI								OFF	ON		
	150ms LO / 150ms HI								ON	ON		

★ Manufacture setting

V7E/LX7-CAD5(Pulse/ICT104U/MDB/RS232 A0)

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
★ Pulse Mode		ON	OFF	
★ ICT104U Interface		OFF	ON	
MDB Interface		ON	ON	
RS232 A0 Mode		OFF	OFF	
★ Reserved				ON
				OFF

DIP SWITCHES SETTING : 2(ICT104U)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Interface		OFF	ON	
MDB Interface		ON	ON	
RS232 A0 Mode		OFF	OFF	
★ Reserved				ON
				OFF

DIP SWITCHES SETTING : 2(MDB) Currency Assign Data

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Interface		OFF	ON	
MDB Interface		ON	ON	
RS232 A0 Mode		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

Interface Bill value	Pulse	ICT104U	RS232 A0	MDB
BV1	CAD 5	CAD 5	CAD 5	CAD 5
BV2	CAD 10	CAD 10	CAD 10	CAD 10
BV3	CAD 20	CAD 20	CAD 20	CAD 20
BV4	CAD 50	CAD 50	CAD 50	CAD 50
BV5	CAD 100	CAD 100	CAD 100	CAD 100

DIP SWITCHES SETTING : 2(RS232 A0)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Interface		OFF	ON	
MDB Interface		ON	ON	
★ RS232 A0 Mode		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

RS232 A0 INFORMATION

BillType Data	
Code	Denomination
1	Reserved
2	Reserved
3	CAD 5
4	CAD 10
5	CAD 20
6	CAD 50
7	CAD 100
8	Reserved
9	Reserved

Note : (1) Default setting.

(2) Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.

(3) Remove the front cover and the dip-switch in on the CPU board.

(Please refer to "SW1" setting.)